
KEMET Part Number: Z0603C101APMST



KEMET, Z-PMS, Ferrite Beads, Noise Suppression, 50 mOhms



| Dimensions | | |
|------------|-----------------|--|
| Chip Size | 0603 | |
| L | 1.6mm +/-0.15mm | |
| W | 0.8mm +/-0.15mm | |
| Т | 0.8mm +/-0.15mm | |
| В | 0.3mm +/-0.2mm | |

| Packaging Specifications | |
|--------------------------|------|
| Packaging: | T&R |
| Packaging Quantity: | 4000 |

| General Information | |
|---------------------|---|
| Series: | Z-PMS |
| Style: | SMD Chip |
| Description: | Chip Bead, Power Line |
| Features: | Suppresses The XL Component; Helps Stop The Reduction Of The Wave-Form Integrity |
| RoHS: | Yes |
| Notes: | Low Rdc Values Reduce Power Dissipation And Extend Battery Life, No Need For Grounding Provides Greater Ciruit Design Felixbility |

| Specifications | | |
|----------------------|--------------------|--|
| Impedance: | 100 Ohms (100 mHz) | |
| Impedance Tolerance: | 25% | |
| Ripple Current: | 1700 mA (MAX) | |
| Temperature Range: | -55/+85°C | |
| Resistance: | 0.05 Ohms | |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

Downloaded From Oneyac.com



单击下面可查看定价,库存,交付和生命周期等信息

>>KEMET(基美)