**Product data sheet** 

## 1. General description

The 74LV132-Q100 is a low-voltage Si-gate CMOS device that is pin and function compatible with 74HC132-Q100 and 74HCT132-Q100.

The 74LV132-Q100 contains four 2-input NAND gates which accept standard input signals. These gates are capable of transforming slowly changing input signals into sharply defined, jitter-free output signals.

The gate switches at different points for positive and negative-going signals. The difference between the positive voltage  $V_{T+}$  and the negative voltage  $V_{T-}$  is defined as the input hysteresis voltage  $V_{H-}$ .

This product has been qualified to the Automotive Electronics Council (AEC) standard Q100 (Grade 1) and is suitable for use in automotive applications.

### 2. Features and benefits

- Automotive product qualification in accordance with AEC-Q100 (Grade 1)
  - Specified from -40 °C to +85 °C and from -40 °C to +125 °C
- Wide operating voltage: 1.0 V to 5.5 V
- Optimized for low voltage applications: 1.0 V to 3.6 V
- Accepts TTL input levels between V<sub>CC</sub> = 2.7 V and V<sub>CC</sub> = 3.6 V
- Typical output ground bounce < 0.8 V at V<sub>CC</sub> = 3.3 V and T<sub>amb</sub> = 25 °C
- Typical HIGH-level output voltage ( $V_{OH}$ ) undershoot: > 2 V at  $V_{CC}$  = 3.3 V and  $T_{amb}$  = 25 °C
- ESD protection:
  - HBM: ANSI/ESDA/JEDEC JS-001 class 2 exceeds 2000 V
  - CDM: ANSI/ESDA/JEDEC JS-002 class C3 exceeds 1000 V
- Multiple package options
- DHVQFN package with Side-Wettable Flanks enabling Automatic Optical Inspection (AOI) of solder joints

# 3. Applications

- Wave and pulse shapers for highly noisy environments
- · Astable multivibrators
- Monostable multivibrators




# 4. Ordering information

**Table 1. Ordering information** 


Type number	Package						
	Temperature range	Name	Description	Version			
74LV132D-Q100	-40 °C to +125 °C	SO14	plastic small outline package; 14 leads; body width 3.9 mm	SOT108-1			
74LV132PW-Q100	-40 °C to +125 °C	TSSOP14	plastic thin shrink small outline package; 14 leads; body width 4.4 mm	SOT402-1			
74LV132BQ-Q100	-40 °C to +125 °C	DHVQFN14	plastic dual in-line compatible thermal enhanced very thin quad flat package; no leads; 14 terminals; body 2.5 × 3 × 0.85 mm	SOT762-1			

# 5. Functional diagram



# 6. Pinning information

### 6.1. Pinning



### 6.2. Pin description

Table 2. Pin description

Symbol	Pin	Description
1A, 2A, 3A, 4A	1, 4, 9, 12	data input
1B, 2B, 3B, 4B	2, 5, 10, 13	data input
1Y, 2Y, 3Y, 4Y	3, 6, 8, 11	data output
GND	7	ground (0 V)
V <sub>CC</sub>	14	supply voltage

# 7. Functional description

#### Table 3. Function table

 $H = HIGH \ voltage \ level; \ L = LOW \ voltage \ level.$ 

Input	Output	
nA	nB	nY
L	L	Н
L	Н	Н
Н	L	Н
Н	Н	L

# 8. Limiting values

#### **Table 4. Limiting values**

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Max	Unit
V <sub>CC</sub>	supply voltage		-0.5	+7.0	V
I <sub>IK</sub>	input clamping current	$V_1 < -0.5 \text{ V or } V_1 > V_{CC} + 0.5 \text{ V}$ [1]	-	±20	mA
I <sub>OK</sub>	output clamping current	$V_O < -0.5 \text{ V or } V_O > V_{CC} + 0.5 \text{ V}$ [1]	-	±50	mA
Io	output current	$V_O = -0.5 \text{ V to } (V_{CC} + 0.5 \text{ V})$	-	±25	mA
I <sub>CC</sub>	supply current		-	50	mA
I <sub>GND</sub>	ground current		-50	-	mA
T <sub>stg</sub>	storage temperature		-65	+150	°C
P <sub>tot</sub>	total power dissipation	$T_{amb} = -40  ^{\circ}\text{C} \text{ to } +125  ^{\circ}\text{C}$ [2]	-	500	mW

<sup>[1]</sup> The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

# 9. Recommended operating conditions

#### Table 5. Recommended operating conditions

Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
V <sub>CC</sub>	supply voltage	[1]	1.0	3.3	5.5	V
VI	input voltage		0	-	V <sub>CC</sub>	V
Vo	output voltage		0	-	V <sub>CC</sub>	V
T <sub>amb</sub>	ambient temperature		-40	+25	+125	°C

<sup>[1]</sup> The static characteristics are guaranteed from  $V_{CC}$  = 1.2 V to  $V_{CC}$  = 5.5 V, but LV devices are guaranteed to function down to  $V_{CC}$  = 1.0 V (with input levels GND or  $V_{CC}$ ).

<sup>[2]</sup> For SOT108-1 (SO14) package: P<sub>tot</sub> derates linearly with 10.1 mW/K above 100 °C.

For SOT402-1 (TSSOP14) package: Ptot derates linearly with 7.3 mW/K above 81 °C.

For SOT762-1 (DHVQFN14) package: Ptot derates linearly with 9.6 mW/K above 98 °C.

# 10. Static characteristics

#### **Table 6. Static characteristics**

Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	-40	-40 °C to +85 °C			-40 °C to +125 °C	
			Min	Typ [1]	Max	Min	Max	
V <sub>OH</sub>	HIGH-level output	$V_I = V_{T+}$ or $V_{T-}$						
	voltage	I <sub>O</sub> = -100 μA; V <sub>CC</sub> = 1.2 V	-	1.2	-	-	-	V
		I <sub>O</sub> = -100 μA; V <sub>CC</sub> = 2.0 V	1.8	2.0	-	1.8	-	V
		$I_{O}$ = -100 $\mu$ A; $V_{CC}$ = 2.7 $V$	2.5	2.7	-	2.5	-	V
		$I_{O}$ = -100 $\mu$ A; $V_{CC}$ = 3.0 $V$	2.8	3.0	-	2.8	-	V
		$I_{O}$ = -100 $\mu$ A; $V_{CC}$ = 4.5 $V$	4.3	4.5	-	4.3	-	V
		$I_{O}$ = -6 mA; $V_{CC}$ = 3.0 V	2.4	2.82	-	2.2	-	V
		I <sub>O</sub> = -12 mA; V <sub>CC</sub> = 4.5 V	3.6	4.2	-	3.5	-	V
V <sub>OL</sub>	LOW-level output voltage	$V_I = V_{T+}$ or $V_{T-}$						
		I <sub>O</sub> = 100 μA; V <sub>CC</sub> = 1.2 V	-	0	-	-	-	V
		I <sub>O</sub> = 100 μA; V <sub>CC</sub> = 2.0 V	-	0	0.2	-	0.2	V
		I <sub>O</sub> = 100 μA; V <sub>CC</sub> = 2.7 V	-	0	0.2	-	0.2	V
		I <sub>O</sub> = 100 μA; V <sub>CC</sub> = 3.0 V	-	0	0.2	-	0.2	V
		I <sub>O</sub> = 100 μA; V <sub>CC</sub> = 4.5 V	-	0	0.2	-	0.2	V
		I <sub>O</sub> = 6 mA; V <sub>CC</sub> = 3.0 V	-	0.25	0.40	-	0.50	V
		I <sub>O</sub> = 12 mA; V <sub>CC</sub> = 4.5 V	-	0.35	0.55	-	0.65	V
l <sub>l</sub>	input leakage current	$V_I = V_{CC}$ or GND; $V_{CC} = 5.5 \text{ V}$	-	-	1.0	-	1.0	μA
I <sub>CC</sub>	supply current	$V_I = V_{CC}$ or GND; $I_O = 0$ A; $V_{CC} = 5.5 \text{ V}$	-	-	20.0	-	40	μA
Δl <sub>CC</sub>	additional supply current	per input; V <sub>I</sub> = V <sub>CC</sub> - 0.6 V; V <sub>CC</sub> = 2.7 V to 3.6 V	-	-	500	-	850	μA
Cı	input capacitance		-	3.5	-	-	-	pF

<sup>[1]</sup> Typical values are measured at  $T_{amb}$  = 25 °C.

# 11. Dynamic characteristics

#### **Table 7. Dynamic characteristics**

GND = 0 V; For test circuit see Fig. 5.

Symbol	Parameter	Conditions		-40	°C to +85	s °C	-40 °C to	Unit	
				Min	Typ [1]	Max	Min	Max	
t <sub>pd</sub>	propagation	nA, nB to nY; see Fig. 4	[2]						
	delay	V <sub>CC</sub> = 1.2 V		-	65	-	-	-	ns
		V <sub>CC</sub> = 2.0 V		-	18	34	-	43	ns
		V <sub>CC</sub> = 2.7 V		-	15	24	-	30	ns
		$V_{CC}$ = 3.0 V to 3.6 V; $C_L$ = 15 pF	[3]	-	10	-	-	-	ns
		V <sub>CC</sub> = 3.0 V to 3.6 V	[3]	-	12	20	-	25	ns
		V <sub>CC</sub> = 4.5 V to 5.5 V	[3]	-	9.0	14	-	17	ns
C <sub>PD</sub>	power dissipation capacitance	$C_L$ = 50 pF; $f_i$ = 1 MHz; $V_I$ = GND to $V_{CC}$	[4]	-	24	-	-	-	pF

- All typical values are measured at  $T_{amb}$  = 25 °C.
- [2] t<sub>pd</sub> is the same as t<sub>PLH</sub> and t<sub>PHL</sub>.
   [3] Typical values are measured at nominal supply voltage (V<sub>CC</sub> = 3.3 V and V<sub>CC</sub> = 5.0 V).
   [4] C<sub>PD</sub> is used to determine the dynamic power dissipation (P<sub>D</sub> in μW).
   P<sub>D</sub> = C<sub>PD</sub> × V<sub>CC</sub> <sup>2</sup> × f<sub>i</sub> × N + Σ(C<sub>L</sub> × V<sub>CC</sub> <sup>2</sup> × f<sub>o</sub>) where:

$$P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \Sigma (C_1 \times V_{CC}^2 \times f_0)$$
 where

f<sub>i</sub> = input frequency in MHz, f<sub>o</sub> = output frequency in MHz


C<sub>L</sub> = output load capacitance in pF

V<sub>CC</sub> = supply voltage in V

N = number of inputs switching

 $\Sigma(C_L \times V_{CC}^2 \times f_o)$  = sum of the outputs.

#### 11.1. Waveforms and test circuit




Measurement points are given in Table 8.

 $V_{\text{OL}}$  and  $V_{\text{OH}}$  are typical voltage output levels that occur with the output load.

#### Fig. 4. The input (nA, nB) to output (nY) propagation delays

#### **Table 8. Measurement points**

Supply voltage	Input	Output
V <sub>CC</sub>	V <sub>M</sub>	V <sub>M</sub>
< 2.7 V	0.5V <sub>CC</sub>	0.5V <sub>CC</sub>
2.7 V to 3.6 V	1.5 V	1.5 V
≥ 4.5 V	0.5V <sub>CC</sub>	0.5V <sub>CC</sub>



Test data is given in Table 9.

Definitions test circuit:

 $R_{T}$  = Termination resistance should be equal to output impedance  $Z_{o}$  of the pulse generator;

R<sub>L</sub> = Load resistance;

 $C_L$  = Load capacitance including jig and probe capacitance.

Fig. 5. Test circuit for measuring switching times

#### Table 9. Test data

Supply voltage	Input		
V <sub>CC</sub>	V <sub>I</sub>	$t_r, t_f$	
< 2.7 V	V <sub>CC</sub>	≤ 2.5 ns	
2.7 V to 3.6 V	2.7 V	≤ 2.5 ns	
≥ 4.5 V	V <sub>CC</sub>	≤ 2.5 ns	

# 12. Transfer characteristics


**Table 10. Transfer characteristics** 


GND = 0 V; See Fig. 6 to Fig. 10.


Symbol	Parameter	Conditions	-4	-40 °C to +85 °C			-40 °C to +125 °C	
			Min	Typ [1]	Max	Min	Max	
V <sub>T+</sub>	positive-going	see Fig. 6 to Fig. 10						
	threshold voltage	V <sub>CC</sub> = 1.2 V	-	0.70	-	-	-	V
		V <sub>CC</sub> = 2.0 V	0.8	1.10	1.4	0.8	1.4	V
		V <sub>CC</sub> = 2.7 V	1.0	1.45	2.0	1.0	2.0	V
		V <sub>CC</sub> = 3.0 V	1.2	1.60	2.2	1.2	2.2	V
		V <sub>CC</sub> = 3.6 V	1.5	1.95	2.4	1.5	2.4	V
		V <sub>CC</sub> = 4.5 V	1.7	2.50	3.2	1.7	3.2	V
		V <sub>CC</sub> = 5.5 V	2.1	3.00	3.9	2.1	3.9	V
V <sub>T-</sub>	negative-going threshold voltage	see Fig. 6 to Fig. 10						
		V <sub>CC</sub> = 1.2 V	-	0.34	-	-	-	V
		V <sub>CC</sub> = 2.0 V	0.3	0.65	0.9	0.3	0.9	V
		V <sub>CC</sub> = 2.7 V	0.4	0.90	1.4	0.4	1.4	V
		V <sub>CC</sub> = 3.0 V	0.6	1.05	1.5	0.6	1.5	V
		V <sub>CC</sub> = 3.6 V	0.8	1.30	1.8	0.8	1.8	V
		V <sub>CC</sub> = 4.5 V	0.9	1.60	2.0	0.9	2.0	V
		V <sub>CC</sub> = 5.5 V	1.2	2.00	2.6	1.2	2.6	V
V <sub>H</sub>	hysteresis voltage	(V <sub>T+</sub> - V <sub>T-</sub> ); see <u>Fig. 6</u> to <u>Fig. 10</u>						
		V <sub>CC</sub> = 1.2 V	-	0.3	-	-	-	V
		V <sub>CC</sub> = 2.0 V	0.2	0.55	8.0	0.2	0.8	V
		V <sub>CC</sub> = 2.7 V	0.3	0.60	1.1	0.3	1.1	V
		V <sub>CC</sub> = 3.0 V	0.4	0.65	1.2	0.4	1.2	V
		V <sub>CC</sub> = 3.6 V	0.4	0.70	1.2	0.4	1.2	V
		V <sub>CC</sub> = 4.5 V	0.4	0.80	1.4	0.4	1.4	V
		V <sub>CC</sub> = 5.5 V	0.6	1.00	1.5	0.6	1.5	V

<sup>[1]</sup> All typical values are measured at  $T_{amb}$  = 25 °C.

### 12.1. Waveforms transfer characteristics







# 13. Package outline




Fig. 11. Package outline SOT108-1 (SO14)

Nexperia 74LV132-Q100

#### **Quad 2-input NAND Schmitt trigger**




Fig. 12. Package outline SOT402-1 (TSSOP14)

Nexperia 74LV132-Q100

#### **Quad 2-input NAND Schmitt trigger**




Fig. 13. Package outline SOT762-1 (DHVQFN14)

Nexperia 74LV132-Q100

### **Quad 2-input NAND Schmitt trigger**

# 14. Abbreviations

#### **Table 11. Abbreviations**

Acronym	Description
CDM	Charged Device Model
CMOS	Complementary Metal Oxide Semiconductor
DUT	Device Under Test
ESD	ElectroStatic Discharge
НВМ	Human Body Model
TTL	Transistor-Transistor Logic

# 15. Revision history

### Table 12. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes	
74LV132_Q100 v.3	20240130	Product data sheet	-	74LV132_Q100 v.2	
Modifications:	<ul> <li>Section 2: ESD specification updated according to the latest JEDEC standard.</li> <li>Fig. 11, Fig. 12: Aligned SO and TSSOP package outline drawings to JEDEC MS-0 and MO-153</li> </ul>				
74LV132_Q100 v.2	20200520	Product data sheet	-	74LV132_Q100 v.1	
Modifications:	guidelines o Legal texts I Section 2 up Table 4: Der	nat of this data sheet has been redesigned to comply with the identity es of Nexperia.  xts have been adapted to the new company name where appropriate.			
74LV132_Q100 v.1	20131111	Product data sheet	-	-	

## 16. Legal information

#### Data sheet status

Document status [1][2]	Product status [3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

- Please consult the most recently issued document before initiating or completing a design.
- [2] The term 'short data sheet' is explained in section "Definitions".
- The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the internet at <a href="https://www.nexperia.com">https://www.nexperia.com</a>.

#### **Definitions**

**Draft** — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. Nexperia does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local Nexperia sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between Nexperia and its customer, unless Nexperia and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the Nexperia product is deemed to offer functions and qualities beyond those described in the Product data sheet.

#### **Disclaimers**

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, Nexperia does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. Nexperia takes no responsibility for the content in this document if provided by an information source outside of Nexperia.

In no event shall Nexperia be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, Nexperia's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of Nexperia.

Right to make changes — Nexperia reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

**Suitability for use in automotive applications** — This Nexperia product has been qualified for use in automotive applications. Unless otherwise agreed in writing, the product is not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or

equipment, nor in applications where failure or malfunction of an Nexperia product can reasonably be expected to result in personal injury, death or severe property or environmental damage. Nexperia and its suppliers accept no liability for inclusion and/or use of Nexperia products in such equipment or applications and therefore such inclusion and/or use is at the customer's own triple.

**Quick reference data** — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

**Applications** — Applications that are described herein for any of these products are for illustrative purposes only. Nexperia makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using Nexperia products, and Nexperia accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the Nexperia product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

Nexperia does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using Nexperia products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). Nexperia does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — Nexperia products are sold subject to the general terms and conditions of commercial sale, as published at <a href="http://www.nexperia.com/profile/terms">http://www.nexperia.com/profile/terms</a>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. Nexperia hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of Nexperia products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

**Export control** — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

**Translations** — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

#### **Trademarks**

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

74LV132\_Q100

Product data sheet

All information provided in this document is subject to legal disclaimers.

© Nexperia B.V. 2024. All rights reserved

### **Contents**

1. General description	1
2. Features and benefits	1
3. Applications	1
4. Ordering information	2
5. Functional diagram	2
6. Pinning information	3
6.1. Pinning	3
6.2. Pin description	3
7. Functional description	3
8. Limiting values	4
9. Recommended operating conditions	4
10. Static characteristics	5
11. Dynamic characteristics	€
11.1. Waveforms and test circuit	7
12. Transfer characteristics	8
12.1. Waveforms transfer characteristics	9
13. Package outline	10
14. Abbreviations	13
15. Revision history	13
16. Legal information	14

For more information, please visit: http://www.nexperia.com For sales office addresses, please send an email to: salesaddresses@nexperia.com Date of release: 30 January 2024

<sup>©</sup> Nexperia B.V. 2024. All rights reserved

# 单击下面可查看定价,库存,交付和生命周期等信息

>>Nexperia(安世)