

# NCV4276, NCV4276A

## 400 mA Low-Drop Voltage Regulator

The NCV4276 is a 400 mA output current integrated low dropout regulator family designed for use in harsh automotive environments. It includes wide operating temperature and input voltage ranges. The device is offered with fixed output voltage options of 1.8 V and 2.5 V with 4% output voltage accuracy while the 3.3 V, 5.0 V, and adjustable voltage versions are available either in 2% or 4% output voltage accuracy. It has a high peak input voltage tolerance and reverse input voltage protection. It also provides overcurrent protection, overtemperature protection and inhibit for control of the state of the output voltage. The NCV4276 family is available in DPAK and D<sup>2</sup>PAK surface mount packages. The output is stable over a wide output capacitance and ESR range.


### Features

- 2.5 V and 1.8 V  $\pm 4\%$  Output Voltage
- 3.3 V, 5.0 V, and Adjustable Voltage Version (from 2.5 V to 20 V)  $\pm 4\%$  or  $\pm 2\%$  Output Voltage
- 400 mA Output Current
- 500 mV (max) Dropout Voltage (5.0 V Output)
- Inhibit Input
- Very Low Current Consumption
- Fault Protection
  - ◆ +45 V Peak Transient Voltage
  - ◆ -42 V Reverse Voltage
  - ◆ Short Circuit
  - ◆ Thermal Overload
- NCV Prefix for Automotive and Other Applications Requiring Site and Control Changes
- These are Pb-Free Devices




**ON Semiconductor®**

<http://onsemi.com>



**DPAK  
5-PIN  
DT SUFFIX  
CASE 175AA**



**D<sup>2</sup>PAK  
5-PIN  
DS SUFFIX  
CASE 936A**

### DEVICE MARKING INFORMATION

See general marking information in the device marking section on page 22 of this data sheet.

### ORDERING INFORMATION

See detailed ordering and shipping information in the ordering information section on page 23 of this data sheet.

# NCV4276, NCV4276A




Figure 1. 4276 Block Diagram




Figure 2. 4276 Adjustable Block Diagram

# NCV4276, NCV4276A

## PIN FUNCTION DESCRIPTION

| Pin No. | Symbol  | Description  |
|---------|---------|--|
| 1       | I       | Input; Battery Supply Input Voltage.   |
| 2       | INH     | Inhibit; Set low-to inhibit.   |
| 3       | GND     | Ground; Pin 3 internally connected to heatsink.  |
| 4       | NC / VA | Not connected for fixed voltage version / Voltage Adjust Input for adjustable voltage version; use an external voltage divider to set the output voltage |
| 5       | Q       | Output: Bypass with a capacitor to GND. See Figures 3 to 8 and Regulator Stability Considerations section.   |

## MAXIMUM RATINGS\*

| Rating                        | Symbol                 | Min  | Max  | Unit |
|-------------------------------|------------------------|--|------|------|
| Input Voltage                 | $V_I$                  | -42  | 45   | V    |
| Input Peak Transient Voltage  | $V_I$                  | -  | 45   | V    |
| Inhibit INH Voltage           | $V_{INH}$              | -42  | 45   | V    |
| Voltage Adjust Input VA       | $V_{VA}$               | -0.3                                       | 10   | V    |
| Output Voltage                | $V_Q$                  | -1.0                                       | 40   | V    |
| Ground Current                | $I_q$                  | -  | 100  | mA   |
| Input Voltage Operating Range | $V_I$                  | $V_Q + 0.5 \text{ V}$ or 4.5 V<br>(Note 1) | 40   | V    |
| ESD Susceptibility            | (Human Body Model)     | -  | 4.5  | kV   |
|                               | (Machine Model)        | -  | 250  | V    |
|                               | (Charged Device Model) | -  | 1.25 | kV   |
| Junction Temperature          | $T_J$                  | -40  | 150  | °C   |
| Storage Temperature           | $T_{stg}$              | -50  | 150  | °C   |

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

\*During the voltage range which exceeds the maximum tested voltage of I, operation is assured, but not specified. Wider limits may apply. Thermal dissipation must be observed closely.

## LEAD TEMPERATURE SOLDERING REFLOW (Note 2)

| Lead Temperature Soldering  | $T_{SLD}$ |   |     | °C |
|---|-----------|---|-----|----|
| Reflow (SMD styles only), Leaded, 60–150 s above 183, 30 s max at peak    |           | - | 240 |    |
| Reflow (SMD styles only), Lead Free, 60–150 s above 217, 40 s max at peak |           | - | 265 |    |
| Wave Solder (through hole styles only), 12 sec max                        |           | - | 310 |    |

## THERMAL CHARACTERISTICS

| Characteristic | Test Conditions (Typical Value) | Unit |
|----------------|---------------------------------|------|
|----------------|---------------------------------|------|

### DPAK 5-PIN PACKAGE

|   | Min Pad Board (Note 3) | 1" Pad Board (Note 4) |     |
|---|------------------------|-----------------------|-----|
| Junction-to-Tab ( $\psi_{JLX}$ , $\psi_{JLX}$ )         | 4.2                    | 4.7                   | C/W |
| Junction-to-Ambient ( $R_{\theta JA}$ , $\theta_{JA}$ ) | 100.9                  | 46.8                  | C/W |

### D<sup>2</sup>PAK 5-PIN PACKAGE

|   | 0.4 sq. in. Spreader Board (Note 5) | 1.2 sq. in. Spreader Board (Note 6) |     |
|---|-------------------------------------|-------------------------------------|-----|
| Junction-to-Tab ( $\psi_{JLX}$ , $\psi_{JLX}$ )         | 3.8                                 | 4.0                                 | C/W |
| Junction-to-Ambient ( $R_{\theta JA}$ , $\theta_{JA}$ ) | 74.8                                | 41.6                                | C/W |

1. Minimum  $V_I = 4.5 \text{ V}$  or ( $V_Q + 0.5 \text{ V}$ ), whichever is higher.
2. Per IPC / JEDEC J-STD-020C.
3. 1 oz. copper, 0.26 inch<sup>2</sup> (168 mm<sup>2</sup>) copper area, 0.062" thick FR4.
4. 1 oz. copper, 1.14 inch<sup>2</sup> (736 mm<sup>2</sup>) copper area, 0.062" thick FR4.
5. 1 oz. copper, 0.373 inch<sup>2</sup> (241 mm<sup>2</sup>) copper area, 0.062" thick FR4.
6. 1 oz. copper, 1.222 inch<sup>2</sup> (788 mm<sup>2</sup>) copper area, 0.062" thick FR4.

# NCV4276, NCV4276A

## ELECTRICAL CHARACTERISTICS ( $V_I = 13.5\text{ V}$ ; $-40^\circ\text{C} < T_J < 150^\circ\text{C}$ ; unless otherwise noted.)

| Characteristic   | Symbol                   | Test Conditions  | NCV4276 |     |       | NCV4276A |     |       | Unit                    |
|--|--------------------------|--|---------|-----|-------|----------|-----|-------|-------------------------|
|  |                          |  | Min     | Typ | Max   | Min      | Typ | Max   |                         |
| <b>OUTPUT</b>  |                          |  |         |     |       |          |     |       |                         |
| Output Voltage, 5.0 V Version  | $V_Q$                    | $5.0\text{ mA} < I_Q < 400\text{ mA}$ ,<br>$6.0\text{ V} < V_I < 28\text{ V}$  | 4.8     | 5.0 | 5.2   | 4.9      | 5.0 | 5.1   | V                       |
| Output Voltage, 5.0 V Version  | $V_Q$                    | $5.0\text{ mA} < I_Q < 200\text{ mA}$ ,<br>$6.0\text{ V} < V_I < 40\text{ V}$  | 4.8     | 5.0 | 5.2   | 4.9      | 5.0 | 5.1   | V                       |
| Output Voltage, 3.3 V Version  | $V_Q$                    | $5.0\text{ mA} < I_Q < 400\text{ mA}$ ,<br>$4.5\text{ V} < V_I < 28\text{ V}$  | 3.168   | 3.3 | 3.432 | 3.234    | 3.3 | 3.366 | V                       |
| Output Voltage, 3.3 V Version  | $V_Q$                    | $5.0\text{ mA} < I_Q < 200\text{ mA}$ ,<br>$4.5\text{ V} < V_I < 40\text{ V}$  | 3.168   | 3.3 | 3.432 | 3.234    | 3.3 | 3.366 | V                       |
| Output Voltage, 2.5 V Version  | $V_Q$                    | $5.0\text{ mA} < I_Q < 400\text{ mA}$ ,<br>$4.5\text{ V} < V_I < 28\text{ V}$  | 2.4     | 2.5 | 2.6   | –        | –   | –     | V                       |
| Output Voltage, 2.5 V Version  | $V_Q$                    | $5.0\text{ mA} < I_Q < 200\text{ mA}$ ,<br>$4.5\text{ V} < V_I < 40\text{ V}$  | 2.4     | 2.5 | 2.6   | –        | –   | –     | V                       |
| Output Voltage, 1.8 V Version  | $V_Q$                    | $5.0\text{ mA} < I_Q < 400\text{ mA}$ ,<br>$4.5\text{ V} < V_I < 28\text{ V}$  | 1.728   | 1.8 | 1.872 | –        | –   | –     | V                       |
| Output Voltage, 1.8 V Version  | $V_Q$                    | $5.0\text{ mA} < I_Q < 200\text{ mA}$ ,<br>$4.5\text{ V} < V_I < 40\text{ V}$  | 1.728   | 1.8 | 1.872 | –        | –   | –     | V                       |
| Output Voltage, Adjustable Version   | $AV_Q$                   | $5.0\text{ mA} < I_Q < 400\text{ mA}$<br>$V_{Q+1} < V_I < 40\text{ V}$<br>$V_I > 4.5\text{ V}$   | –4%     | –   | +4%   | –2%      | –   | +2%   | V                       |
| Output Current Limitation  | $I_Q$                    | $V_Q = 90\% V_{Q\text{TYP}}$ ( $V_{Q\text{TYP}} = 2.5\text{ V}$ for ADJ version)   | 400     | 700 | 1100  | 400      | 700 | 1100  | mA                      |
| Quiescent Current (Sleep Mode)<br>$I_q = I_I - I_Q$  | $I_q$                    | $V_{\text{INH}} = 0\text{ V}$  | –       | –   | 10    | –        | –   | 10    | $\mu\text{A}$           |
| Quiescent Current, $I_q = I_I - I_Q$   | $I_q$                    | $I_Q = 1.0\text{ mA}$  | –       | 130 | 220   | –        | 130 | 200   | $\mu\text{A}$           |
| Quiescent Current, $I_q = I_I - I_Q$   | $I_q$                    | $I_Q = 250\text{ mA}$  | –       | 10  | 15    | –        | 10  | 15    | mA                      |
| Quiescent Current, $I_q = I_I - I_Q$   | $I_q$                    | $I_Q = 400\text{ mA}$  | –       | 25  | 35    | –        | 25  | 35    | mA                      |
| Dropout Voltage,<br>5.0 V Version<br>3.3 V Version<br>2.5 V Version<br>1.8 V Version<br>Adjustable Version | $V_{\text{DR}}$          | $I_Q = 250\text{ mA}$ ,<br>$V_{\text{DR}} = V_I - V_Q$<br>$V_I = 5.0\text{ V}$<br>$V_I = 4.5\text{ V}$<br>$V_I = 4.5\text{ V}$<br>$V_I = 4.5\text{ V}$<br>$V_I > 4.5\text{ V}$ | –       | 250 | 500   | –        | –   | –     | mV<br>V<br>V<br>V<br>mV |
| Dropout Voltage (5.0 V Version)  | $V_{\text{DR}}$          | $I_Q = 250\text{ mA}$ (Note 7)   | –       | –   | –     | –        | 250 | 500   | mV                      |
| Load Regulation  | $\Delta V_{Q,\text{LO}}$ | $I_Q = 5.0\text{ mA}$ to $400\text{ mA}$   | –       | 10  | 35    | –        | 3.0 | 20    | mV                      |
| Line Regulation  | $\Delta V_Q$             | $\Delta V_I = 12\text{ V}$ to $32\text{ V}$ ,<br>$I_Q = 5.0\text{ mA}$   | –       | 2.5 | 25    | –        | 4.0 | 15    | mV                      |
| Power Supply Ripple Rejection  | PSRR                     | $f_r = 100\text{ Hz}$ , $V_r = 0.5\text{ V}_{\text{PP}}$   | –       | 60  | –     | –        | 70  | –     | dB                      |
| Temperature Output Voltage Drift   | $dV_Q/dT$                | –  | –       | 0.5 | –     | –        | 0.5 | –     | mV/K                    |

### INHIBIT

|                                   |                  |                                 |     |     |     |     |     |     |               |
|-----------------------------------|------------------|---------------------------------|-----|-----|-----|-----|-----|-----|---------------|
| Inhibit Voltage, Output High      | $V_{\text{INH}}$ | $V_Q \geq V_{Q\text{MIN}}$      | –   | 2.8 | 3.5 | –   | 2.3 | 2.8 | V             |
| Inhibit Voltage, Output Low (Off) | $V_{\text{INH}}$ | $V_Q \leq 0.1\text{ V}$         | 0.5 | 1.7 | –   | 1.8 | 2.2 | –   | V             |
| Input Current                     | $I_{\text{INH}}$ | $V_{\text{INH}} = 5.0\text{ V}$ | 5.0 | 10  | 20  | 5.0 | 10  | 20  | $\mu\text{A}$ |


### THERMAL SHUTDOWN

|                               |                 |                       |     |   |     |     |   |     |                  |
|-------------------------------|-----------------|-----------------------|-----|---|-----|-----|---|-----|------------------|
| Thermal Shutdown Temperature* | $T_{\text{SD}}$ | $I_Q = 5.0\text{ mA}$ | 150 | – | 210 | 150 | – | 210 | $^\circ\text{C}$ |
|-------------------------------|-----------------|-----------------------|-----|---|-----|-----|---|-----|------------------|


\*Guaranteed by design, not tested in production.

7. Measured when the output voltage  $V_Q$  has dropped 100 mV from the nominal valued obtained at  $V = 13.5\text{ V}$ .

## NCV4276, NCV4276A



**Figure 3. Applications Circuit; Fixed Voltage Version**



$C_b^*$  - Required if usage of low ESR output capacitor  $C_Q$  is demand, see Regulator Stability Considerations section

**Figure 4. Applications Circuit; Adjustable Voltage Version**

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 5. Output Stability with Output Capacitor ESR, 5.0 V, 3.3 V, 2.5 V and 1.8 V Regulator




Figure 6. Output Stability with Output Capacitor ESR, 5.0 V and 3.3 V Regulator




Figure 7. Output Stability with Output Capacitor ESR, 2.5 V and 1.8 V Regulator




Figure 8. Output Stability with Output Capacitor ESR, Adjustable Regulator

TYPICAL PERFORMANCE CHARACTERISTICS – 4276 Version




Figure 9. Output Voltage vs. Junction Temperature, 5.0 V Version




Figure 10. Output Voltage vs. Junction Temperature, 1.8 V Version




Figure 11. Output Voltage vs. Junction Temperature, 2.5 V Version




Figure 12. Output Voltage vs. Junction Temperature, 3.3 V Version




Figure 13. Current Consumption vs. Input Voltage, 5.0 V Version




Figure 14. Current Consumption vs. Input Voltage, 1.8 V Version

TYPICAL PERFORMANCE CHARACTERISTICS – 4276 Version




Figure 15. Current Consumption vs. Input Voltage, 2.5 V Version




Figure 16. Current Consumption vs. Input Voltage, 3.3 V Version




Figure 17. High Voltage Behavior




Figure 18. Dropout Voltage vs. Output Current, 5.0 V Version




Figure 19. Maximum Output Current vs. Input Voltage




Figure 20. Current Consumption vs. Output Current (High Load)



TYPICAL PERFORMANCE CHARACTERISTICS – 4276 Version




Figure 21. Current Consumption vs. Output Current (Low Load)




Figure 22. Output Voltage vs. Input Voltage, 1.8 V Version




Figure 23. Output Voltage vs. Input Voltage, 2.5 V Version




Figure 24. Output Voltage vs. Input Voltage, 3.3 V Version




Figure 25. Output Voltage vs. Input Voltage, 5.0 V Version




Figure 26. Input Current vs. Input Voltage, 5.0 V Version

TYPICAL PERFORMANCE CHARACTERISTICS – 4276 Version




Figure 27. Input Current vs. Input Voltage, 1.8 V Version




Figure 28. Input Current vs. Input Voltage, 2.5 V Version




Figure 29. Input Current vs. Input Voltage, 3.3 V Version

TYPICAL PERFORMANCE CHARACTERISTICS – 4276A Version




Figure 30. Output Voltage vs. Junction Temperature, 5.0 V Version




Figure 31. Output Voltage vs. Junction Temperature, 3.3 V Version




Figure 32. Current Consumption vs. Input Voltage, 5.0 V Version




Figure 33. Current Consumption vs. Input Voltage, 3.3 V Version




Figure 35. Low Voltage Behavior, 5.0 V Version




Figure 34. Low Voltage Behavior, 3.3 V Version

TYPICAL PERFORMANCE CHARACTERISTICS – 4276A Version




Figure 36. Input Current vs. Input Voltage, 5.0 V Version




Figure 37. Input Current vs. Input Voltage, 3.3 V Version




Figure 38. Dropout Voltage vs. Output Current




Figure 39. Maximum Output Current vs. Input Voltage




Figure 40. Current Consumption vs. Output Current (High Load)




Figure 41. Current Consumption vs. Output Current (Low Load)

TYPICAL PERFORMANCE CHARACTERISTICS – Adjustable Version




Figure 42. Output Voltage vs. Junction Temperature, Adjustable Version




Figure 43. Current Consumption vs. Input Voltage, Adjustable Version




Figure 44. Low Voltage Behavior, Adjustable Version




Figure 45. High Voltage Behavior, Adjustable Version

TYPICAL PERFORMANCE CHARACTERISTICS – Adjustable Version




Figure 46. Dropout Voltage vs. Output Current, Regulator Set at 5.0 V, Adjustable Version




Figure 47. Maximum Output Current vs. Input Voltage, Adjustable Version




Figure 48. Current Consumption vs. Output Current (High Load), Adjustable Version




Figure 49. Current Consumption vs. Output Current (Low Load), Adjustable Version

**Circuit Description**

The NCV4276 is an integrated low dropout regulator that provides a regulated voltage at 400 mA to the output. It is enabled with an input to the inhibit pin. The regulator voltage is provided by a PNP pass transistor controlled by an error amplifier with a bandgap reference, which gives it the lowest possible dropout voltage. The output current capability is 400 mA, and the base drive quiescent current is controlled to prevent oversaturation when the input voltage is low or when the output is overloaded. The regulator is protected by both current limit and thermal shutdown. Thermal shutdown occurs above 150°C to protect the IC during overloads and extreme ambient temperatures.

**Regulator**

The error amplifier compares the reference voltage to a sample of the output voltage (V<sub>O</sub>) and drives the base of a PNP series pass transistor via a buffer. The reference is a bandgap design to give it a temperature-stable output. Saturation control of the PNP is a function of the load current and input voltage. Oversaturation of the output power device is prevented, and quiescent current in the ground pin is minimized. See Figure 4, Test Circuit, for circuit element nomenclature illustration.

**Regulator Stability Considerations**

The input capacitors (C<sub>I1</sub> and C<sub>I2</sub>) are necessary to stabilize the input impedance to avoid voltage line influences. Using a resistor of approximately 1.0 Ω in series with C<sub>I2</sub> can stop potential oscillations caused by stray inductance and capacitance.

The output capacitor helps determine three main characteristics of a linear regulator: startup delay, load transient response and loop stability. The capacitor value and type should be based on cost, availability, size and temperature constraints. The aluminum electrolytic capacitor is the least expensive solution, but, if the circuit operates at low temperatures (–25°C to –40°C), both the value and ESR of the capacitor will vary considerably. The capacitor manufacturer’s data sheet usually provides this information.

The value for the output capacitor C<sub>O</sub>, shown in Figure 3, should work for most applications; see also Figures 5 to 8 for output stability at various load and Output Capacitor ESR conditions. Stable region of ESR in Figures 5 to 8 shows ESR values at which the LDO output voltage does not have any permanent oscillations at any dynamic changes of output load current. Marginal ESR is the value at which the output voltage waving is fully damped during four periods after the load change and no oscillation is further observable.

ESR characteristics were measured with ceramic capacitors and additional series resistors to emulate ESR. Low duty cycle pulse load current technique has been used to maintain junction temperature close to ambient temperature.

Minimum ESR for C<sub>O</sub> = 22 μF is native ESR of ceramic capacitor with which the fixed output voltage devices are performing stable. Murata ceramic capacitors were used, GRM32ER71C226KE18 (22 μF, 16 V, X7R, 1210), GRM31CR71C106KAC7 (10 μF, 16 V, X7R, 1206).

**Calculating Bypass Capacitor**

If usage of low ESR ceramic capacitors is demand in case of Adjustable Regulator, connect the bypass capacitor C<sub>b</sub> between Voltage Adjust pin and Q pin according to Applications circuit at Figure 4.

Parallel combination of bypass capacitor C<sub>b</sub> with the feedback resistor R<sub>1</sub> contributes in the device transfer function as an additional zero and affects the device loop stability, therefore its value must be optimized. Attention to the Output Capacitor value and its ESR must be paid. See also Stability in High Speed Linear LDO Regulators Application Note, AND8037/D for more information.

Optimal value of bypass capacitor is given by following expression

$$C_b = \frac{1}{2 \times \pi \times f_z \times R_1} \cdot (F)$$

where

R<sub>1</sub> = the upper feedback resistor

f<sub>z</sub> = the frequency of the zero added into the device transfer function by R<sub>1</sub> and C<sub>b</sub> external components.

Set the R<sub>1</sub> resistor according to output voltage requirement. Chose the f<sub>z</sub> with regard on the output capacitance C<sub>O</sub>, refer to the table below.

|                            |         |         |         |        |
|----------------------------|---------|---------|---------|--------|
| C <sub>O</sub> (μF)        | 10      | 22      | 47      | 100    |
| f <sub>z</sub> Range (kHz) | 20 - 50 | 14 - 35 | 10 - 20 | 7 - 14 |

Ceramic capacitors and its part numbers listed bellow have been used as low ESR output capacitors C<sub>O</sub> from the table above to define the frequency ranges of additional zero required for stability.

GRM31CR71C106KAC7 (10 μF, 16 V, X7R, 1206)

GRM32ER71C226KE18 (22 μF, 16 V, X7R, 1210)

GRM32ER61C476ME15 (47 μF, 16 V, X5R, 1210)

GRM32ER60J107ME20 (100 μF, 6.3 V, X5R, 1210)

**Inhibit Input**

The inhibit pin is used to turn the regulator on or off. By holding the pin down to a voltage less than 0.5 V (or 1.8 V for NCV4276A parts), the output of the regulator will be turned off. During startup transient the regulator is off at input voltage slew rates faster than 30 V/μs. When the voltage on the Inhibit pin is greater than 3.5 V (or 2.8 V for NCV4276A parts), the output of the regulator will be enabled to power its output to the regulated output voltage. The inhibit pin may be connected directly to the input pin to give constant enable to the output regulator.

## NCV4276, NCV4276A

### Setting the Output Voltage (Adjustable Version)

The output voltage range of the adjustable version can be set between 2.5 V and 20 V. This is accomplished with an external resistor divider feeding back the voltage to the IC back to the error amplifier by the voltage adjust pin VA. The internal reference voltage is set to a temperature stable reference of 2.5 V.

The output voltage is calculated from the following formula. Ignoring the bias current into the VA pin:

$$V_Q = [(R1 + R2) * V_{ref}] / R2$$

Use  $R2 < 50 \text{ k}$  to avoid significant voltage output errors due to VA bias current.

Connecting VA directly to Q without R1 and R2 creates an output voltage of 2.5 V.

Designers should consider the tolerance of R1 and R2 during the design phase.

The input voltage range for operation (pin 1) of the adjustable version is between  $(V_Q + 0.5 \text{ V})$  and 40 V. Internal bias requirements dictate a minimum input voltage of 4.5 V. The dropout voltage for output voltages less than 4.0 V is  $(4.5 \text{ V} - V_Q)$ .



**Calculating Power Dissipation in a Single Output Linear Regulator**

The maximum power dissipation for a single output regulator (Figure 50) is:

$$PD(max) = [V_{I(max)} - V_{Q(min)}] I_{Q(max)} + V_{I(max)} I_q \tag{1}$$

where

- $V_{I(max)}$  is the maximum input voltage,
- $V_{Q(min)}$  is the minimum output voltage,
- $I_{Q(max)}$  is the maximum output current for the application,
- $I_q$  is the quiescent current the regulator consumes at  $I_{Q(max)}$ .

Once the value of  $P_{D(max)}$  is known, the maximum permissible value of  $R_{\theta JA}$  can be calculated:

$$R_{\theta JA} = \frac{150^{\circ}C - T_A}{P_D} \tag{2}$$

The value of  $R_{\theta JA}$  can then be compared with those in the package section of the data sheet. Those packages with  $R_{\theta JA}$  less than the calculated value in Equation 2 will keep the die temperature below 150°C.

In some cases, none of the packages will be sufficient to dissipate the heat generated by the IC, and an external heatsink will be required.

**Heatsinks**

A heatsink effectively increases the surface area of the package to improve the flow of heat away from the IC and into the surrounding air.

Each material in the heat flow path between the IC and the outside environment will have a thermal resistance. Like series electrical resistances, these resistances are summed to determine the value of  $R_{\theta JA}$ :


$$R_{\theta JA} = R_{\theta JC} + R_{\theta CS} + R_{\theta SA} \tag{3}$$

where

- $R_{\theta JC}$  is the junction-to-case thermal resistance,
- $R_{\theta CS}$  is the case-to-heatsink thermal resistance,
- $R_{\theta SA}$  is the heatsink-to-ambient thermal resistance.

$R_{\theta JC}$  appears in the package section of the data sheet. Like  $R_{\theta JA}$ , it too is a function of package type.  $R_{\theta CS}$  and  $R_{\theta SA}$  are functions of the package type, heatsink and the interface between them. These values appear in data sheets of heatsink manufacturers.

Thermal, mounting, and heatsinking considerations are discussed in the ON Semiconductor application note AN1040/D.



**Figure 50. Single Output Regulator with Key Performance Parameters Labeled**

# NCV4276, NCV4276A


## Thermal Model

A discussion of thermal modeling is in the ON Semiconductor web site: <http://www.onsemi.com/pub/collateral/BR1487-D.PDF>.


**Table 1. DPAK 5-Lead Thermal RC Network Models**

| Drain Copper Area (1 oz thick) |                 |              | 168 mm <sup>2</sup> | 736 mm <sup>2</sup> |       | 168 mm <sup>2</sup> | 736 mm <sup>2</sup> |       |
|--------------------------------|-----------------|--------------|---------------------|---------------------|-------|---------------------|---------------------|-------|
| (SPICE Deck Format)            |                 |              | Cauer Network       |                     |       | Foster Network      |                     |       |
|                                |                 |              | 168 mm <sup>2</sup> | 736 mm <sup>2</sup> | Units | Tau                 | Tau                 | Units |
| <b>C_C1</b>                    | <b>Junction</b> | <b>GND</b>   | 1.00E-06            | 1.00E-06            | W-s/C | 1.36E-08            | 1.361E-08           | sec   |
| <b>C_C2</b>                    | <b>node1</b>    | <b>GND</b>   | 1.00E-05            | 1.00E-05            | W-s/C | 7.41E-07            | 7.411E-07           | sec   |
| <b>C_C3</b>                    | <b>node2</b>    | <b>GND</b>   | 6.00E-05            | 6.00E-05            | W-s/C | 1.04E-05            | 1.029E-05           | sec   |
| <b>C_C4</b>                    | <b>node3</b>    | <b>GND</b>   | 1.00E-04            | 1.00E-04            | W-s/C | 3.91E-05            | 3.737E-05           | sec   |
| <b>C_C5</b>                    | <b>node4</b>    | <b>GND</b>   | 4.36E-04            | 3.64E-04            | W-s/C | 1.80E-03            | 1.376E-03           | sec   |
| C_C6                           | node5           | GND          | 6.77E-02            | 1.92E-02            | W-s/C | 3.77E-01            | 2.851E-02           | sec   |
| C_C7                           | node6           | GND          | 1.51E-01            | 1.27E-01            | W-s/C | 3.79E+00            | 9.475E-01           | sec   |
| C_C8                           | node7           | GND          | 4.80E-01            | 1.018               | W-s/C | 2.65E+01            | 1.173E+01           | sec   |
| C_C9                           | node8           | GND          | 3.740               | 2.955               | W-s/C | 8.71E+01            | 8.59E+01            | sec   |
| C_C10                          | node9           | GND          | 10.322              | 0.438               | W-s/C |                     |                     | sec   |
|                                |                 |              | 168 mm <sup>2</sup> | 736 mm <sup>2</sup> |       | R's                 | R's                 |       |
| <b>R_R1</b>                    | <b>Junction</b> | <b>node1</b> | 0.015               | 0.015               | C/W   | 0.0123              | 0.0123              | C/W   |
| <b>R_R2</b>                    | <b>node1</b>    | <b>node2</b> | 0.08                | 0.08                | C/W   | 0.0585              | 0.0585              | C/W   |
| <b>R_R3</b>                    | <b>node2</b>    | <b>node3</b> | 0.4                 | 0.4                 | C/W   | 0.0304              | 0.0287              | C/W   |
| <b>R_R4</b>                    | <b>node3</b>    | <b>node4</b> | 0.2                 | 0.2                 | C/W   | 0.3997              | 0.3772              | C/W   |
| <b>R_R5</b>                    | <b>node4</b>    | <b>node5</b> | 2.97519             | 2.6171              | C/W   | 3.115               | 2.68                | C/W   |
| R_R6                           | node5           | node6        | 8.2971              | 1.6778              | C/W   | 3.571               | 1.38                | C/W   |
| R_R7                           | node6           | node7        | 25.9805             | 7.4246              | C/W   | 12.851              | 5.92                | C/W   |
| R_R8                           | node7           | node8        | 46.5192             | 14.9320             | C/W   | 35.471              | 7.39                | C/W   |
| R_R9                           | node8           | node9        | 17.7808             | 19.2560             | C/W   | 46.741              | 28.94               | C/W   |
| R_R10                          | node9           | GND          | 0.1                 | 0.1758              | C/W   |                     |                     | C/W   |

NOTE: Bold face items represent the package without the external thermal system.



**Figure 51. Grounded Capacitor Thermal Network ("Cauer" Ladder)**



**Figure 52. Non-Grounded Capacitor Thermal Ladder ("Foster" Ladder)**

# NCV4276, NCV4276A

**Table 2. D<sup>2</sup>PAK 5-Lead Thermal RC Network Models**

| Drain Copper Area (1 oz thick) |                 |              | 241 mm <sup>2</sup> | 788 mm <sup>2</sup> |       | 241 mm <sup>2</sup> | 788 mm <sup>2</sup> |       |
|--------------------------------|-----------------|--------------|---------------------|---------------------|-------|---------------------|---------------------|-------|
| (SPICE Deck Format)            |                 |              | Cauer Network       |                     |       | Foster Network      |                     |       |
|                                |                 |              | 241 mm <sup>2</sup> | 653 mm <sup>2</sup> | Units | Tau                 | Tau                 | Units |
| <b>C_C1</b>                    | <b>Junction</b> | <b>GND</b>   | 1.00E-06            | 1.00E-06            | W-s/C | 1.361E-08           | 1.361E-08           | sec   |
| <b>C_C2</b>                    | <b>node1</b>    | <b>GND</b>   | 1.00E-05            | 1.00E-05            | W-s/C | 7.411E-07           | 7.411E-07           | sec   |
| <b>C_C3</b>                    | <b>node2</b>    | <b>GND</b>   | 6.00E-05            | 6.00E-05            | W-s/C | 1.005E-05           | 1.007E-05           | sec   |
| <b>C_C4</b>                    | <b>node3</b>    | <b>GND</b>   | 1.00E-04            | 1.00E-04            | W-s/C | 3.460E-05           | 3.480E-05           | sec   |
| <b>C_C5</b>                    | <b>node4</b>    | <b>GND</b>   | 2.82E-04            | 2.87E-04            | W-s/C | 7.868E-04           | 8.107E-04           | sec   |
| C_C6                           | node5           | GND          | 5.58E-03            | 5.95E-03            | W-s/C | 7.431E-03           | 7.830E-03           | sec   |
| C_C7                           | node6           | GND          | 4.25E-01            | 4.61E-01            | W-s/C | 2.786E+00           | 2.012E+00           | sec   |
| C_C8                           | node7           | GND          | 9.22E-01            | 2.05                | W-s/C | 2.014E+01           | 2.601E+01           | sec   |
| C_C9                           | node8           | GND          | 1.73                | 4.88                | W-s/C | 1.134E+02           | 1.218E+02           | sec   |
| C_C10                          | node9           | GND          | 7.12                | 1.31                | W-s/C |                     |                     | sec   |
|                                |                 |              | 241 mm <sup>2</sup> | 653 mm <sup>2</sup> |       | R's                 | R's                 |       |
| <b>R_R1</b>                    | <b>Junction</b> | <b>node1</b> | 0.015               | 0.0150              | C/W   | 0.0123              | 0.0123              | C/W   |
| <b>R_R2</b>                    | <b>node1</b>    | <b>node2</b> | 0.08                | 0.0800              | C/W   | 0.0585              | 0.0585              | C/W   |
| <b>R_R3</b>                    | <b>node2</b>    | <b>node3</b> | 0.4                 | 0.4000              | C/W   | 0.0257              | 0.0260              | C/W   |
| <b>R_R4</b>                    | <b>node3</b>    | <b>node4</b> | 0.2                 | 0.2000              | C/W   | 0.3413              | 0.3438              | C/W   |
| <b>R_R5</b>                    | <b>node4</b>    | <b>node5</b> | 1.85638             | 1.8839              | C/W   | 1.77                | 1.81                | C/W   |
| R_R6                           | node5           | node6        | 1.23672             | 1.2272              | C/W   | 1.54                | 1.52                | C/W   |
| R_R7                           | node6           | node7        | 9.81541             | 5.3383              | C/W   | 4.13                | 3.46                | C/W   |
| R_R8                           | node7           | node8        | 33.1868             | 18.9591             | C/W   | 6.27                | 5.03                | C/W   |
| R_R9                           | node8           | node9        | 27.0263             | 13.3369             | C/W   | 60.80               | 29.30               | C/W   |
| R_R10                          | node9           | GND          | 1.13944             | 0.1191              | C/W   |                     |                     | C/W   |

NOTE: Bold face items represent the package without the external thermal system.

The Cauer networks generally have physical significance and may be divided between nodes to separate thermal behavior due to one portion of the network from another. The Foster networks, though when sorted by time constant (as above) bear a rough correlation with the Cauer networks, are really only convenient mathematical models. Cauer networks can be easily implemented using circuit simulating tools, whereas Foster networks may be more easily implemented using mathematical tools (for instance, in a spreadsheet program), according to the following formula:

$$R(t) = \sum_{i=1}^n R_i (1 - e^{-t/\tau_i})$$

# NCV4276, NCV4276A




Figure 53.  $\theta_{JA}$  vs. Copper Spreader Area, DPAK 5-Lead




Figure 54.  $\theta_{JA}$  vs. Copper Spreader Area, D<sup>2</sup>PAK 5-Lead




Figure 55. Single-Pulse Heating Curves, DPAK 5-Lead




Figure 56. Single-Pulse Heating Curves, D<sup>2</sup>PAK 5-Lead

# NCV4276, NCV4276A




Figure 57. Duty Cycle for 1" Spreader Boards, DPAK 5-Lead






Figure 58. Duty Cycle for 1" Spreader Boards, D<sup>2</sup>PAK 5-Lead

# NCV4276, NCV4276A


## MARKING DIAGRAMS




NCV4276A  
**DPAK**  
**5-PIN**  
**DT SUFFIX**  
**CASE 175AA**



NCV4276A  
**D<sup>2</sup>PAK**  
**5-PIN**  
**DS SUFFIX**  
**CASE 936A**



NCV4276  
**DPAK**  
**5-PIN**  
**DT SUFFIX**  
**CASE 175AA**



NCV4276  
**D<sup>2</sup>PAK**  
**5-PIN**  
**DS SUFFIX**  
**CASE 936A**

\*Tab is connected to Pin 3 on all packages.

A = Assembly Location  
 WL, L = Wafer Lot  
 Y = Year  
 WW = Work Week  
 G = Pb-Free Device  
 x, xx = Voltage Ratings as indicated below

### A-Version

|                        |                        |
|------------------------|------------------------|
| DPAK                   | D <sup>2</sup> PAK     |
| XX = AJ (Adj. Voltage) | XX = AJ (Adj. Voltage) |
| XX = 50 (5.0 V)        | XX = 50 (5.0 V)        |
| XX = 33 (3.3 V)        |                        |

### Non-A-Version

|                      |                        |
|----------------------|------------------------|
| DPAK                 | D <sup>2</sup> PAK     |
| X = V (Adj. Voltage) | XX = AJ (Adj. Voltage) |
| X = 5 (5.0 V)        | XX = 50 (5.0 V)        |
| X = 3 (3.3 V)        | XX = 33 (3.3 V)        |
|                      | XX = 25 (2.5 V)        |
|                      | XX = 18 (1.8 V)        |

# NCV4276, NCV4276A

## ORDERING INFORMATION


| Device           | Output Voltage Accuracy | Output Voltage                      | Package                             | Shipping†          |
|------------------|-------------------------|-------------------------------------|-------------------------------------|--------------------|
| NCV4276DT50RKG   | 4%                      | 5.0 V                               | DPAK, 5-Pin (Pb-Free)               | 2500 / Tape & Reel |
| NCV4276DS50G     |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 50 Units / Rail    |
| NCV4276DS50R4G   |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 800 / Tape & Reel  |
| NCV4276DT33RKG   |                         | 3.3 V                               | DPAK, 5-Pin (Pb-Free)               | 2500 / Tape & Reel |
| NCV4276DS33G     |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 50 Units / Rail    |
| NCV4276DS33R4G   |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 800 / Tape & Reel  |
| NCV4276DS25G     |                         | 2.5 V                               | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 50 Units / Rail    |
| NCV4276DS25R4G   |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 800 / Tape & Reel  |
| NCV4276DS18G     |                         | 1.8 V                               | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 50 Units / Rail    |
| NCV4276DS18R4G   |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 800 / Tape & Reel  |
| NCV4276DTADJRKG  |                         | Adjustable                          | DPAK, 5-Pin (Pb-Free)               | 2500 / Tape & Reel |
| NCV4276DSADJG    |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 50 Units / Rail    |
| NCV4276DSADJR4G  |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 800 / Tape & Reel  |
| NCV4276ADT33RKG  | 2%                      | 3.3 V                               | DPAK, 5-Pin (Pb-Free)               | 2500 / Tape & Reel |
| NCV4276ADT50RKG  |                         | 5.0 V                               | DPAK, 5-Pin (Pb-Free)               | 2500 / Tape & Reel |
| NCV4276ADS50G    |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 50 Units / Rail    |
| NCV4276ADS50R4G  |                         | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 800 / Tape & Reel                   |                    |
| NCV4276ADTADJRKG |                         | Adjustable                          | DPAK, 5-Pin (Pb-Free)               | 2500 / Tape & Reel |
| NCV4276ADSADJG   |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 50 Units / Rail    |
| NCV4276ADSADJR4G |                         |                                     | D <sup>2</sup> PAK, 5-Pin (Pb-Free) | 800 / Tape & Reel  |

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

# NCV4276, NCV4276A

## PACKAGE DIMENSIONS


DPAK 5, CENTER LEAD CROP  
DT SUFFIX  
CASE 175AA-01  
ISSUE A



- NOTES:  
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.  
2. CONTROLLING DIMENSION: INCH.

| DIM | INCHES    |       | MILLIMETERS |      |
|-----|-----------|-------|-------------|------|
|     | MIN       | MAX   | MIN         | MAX  |
| A   | 0.235     | 0.245 | 5.97        | 6.22 |
| B   | 0.250     | 0.265 | 6.35        | 6.73 |
| C   | 0.086     | 0.094 | 2.19        | 2.38 |
| D   | 0.020     | 0.028 | 0.51        | 0.71 |
| E   | 0.018     | 0.023 | 0.46        | 0.58 |
| F   | 0.024     | 0.032 | 0.61        | 0.81 |
| G   | 0.180 BSC |       | 4.56 BSC    |      |
| H   | 0.034     | 0.040 | 0.87        | 1.01 |
| J   | 0.018     | 0.023 | 0.46        | 0.58 |
| K   | 0.102     | 0.114 | 2.60        | 2.89 |
| L   | 0.045 BSC |       | 1.14 BSC    |      |
| R   | 0.170     | 0.190 | 4.32        | 4.83 |
| R1  | 0.185     | 0.210 | 4.70        | 5.33 |
| S   | 0.025     | 0.040 | 0.63        | 1.01 |
| U   | 0.020     | ---   | 0.51        | ---  |
| V   | 0.035     | 0.050 | 0.89        | 1.27 |
| Z   | 0.155     | 0.170 | 3.93        | 4.32 |

### SOLDERING FOOTPRINT\*




\*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.



# NCV4276, NCV4276A

## PACKAGE DIMENSIONS

D<sup>2</sup>PAK 5  
CASE 936A-02  
ISSUE C




NOTES:

1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: INCH.
3. TAB CONTOUR OPTIONAL WITHIN DIMENSIONS A AND K.
4. DIMENSIONS U AND V ESTABLISH A MINIMUM MOUNTING SURFACE FOR TERMINAL 6.
5. DIMENSIONS A AND B DO NOT INCLUDE MOLD FLASH OR GATE PROTRUSIONS. MOLD FLASH AND GATE PROTRUSIONS NOT TO EXCEED 0.025 (0.635) MAXIMUM.

| DIM | INCHES    |       | MILLIMETERS |        |
|-----|-----------|-------|-------------|--------|
|     | MIN       | MAX   | MIN         | MAX    |
| A   | 0.386     | 0.403 | 9.804       | 10.236 |
| B   | 0.356     | 0.368 | 9.042       | 9.347  |
| C   | 0.170     | 0.180 | 4.318       | 4.572  |
| D   | 0.026     | 0.036 | 0.660       | 0.914  |
| E   | 0.045     | 0.055 | 1.143       | 1.397  |
| G   | 0.067 BSC |       | 1.702 BSC   |        |
| H   | 0.539     | 0.579 | 13.691      | 14.707 |
| K   | 0.050 REF |       | 1.270 REF   |        |
| L   | 0.000     | 0.010 | 0.000       | 0.254  |
| M   | 0.088     | 0.102 | 2.235       | 2.591  |
| N   | 0.018     | 0.026 | 0.457       | 0.660  |
| P   | 0.058     | 0.078 | 1.473       | 1.981  |
| R   | 5° REF    |       | 5° REF      |        |
| S   | 0.116 REF |       | 2.946 REF   |        |
| U   | 0.200 MIN |       | 5.080 MIN   |        |
| V   | 0.250 MIN |       | 6.350 MIN   |        |

### SOLDERING FOOTPRINT



SCALE 3:1 (mm/inches)

SMART REGULATOR is a registered trademark of Semiconductor Components Industries, LLC (SCILLC).

**ON Semiconductor** and **ON** are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

### PUBLICATION ORDERING INFORMATION

**LITERATURE FULFILLMENT:**  
Literature Distribution Center for ON Semiconductor  
P.O. Box 5163, Denver, Colorado 80217 USA  
**Phone:** 303-675-2175 or 800-344-3860 Toll Free USA/Canada  
**Fax:** 303-675-2176 or 800-344-3867 Toll Free USA/Canada  
**Email:** orderlit@onsemi.com

**N. American Technical Support:** 800-282-9855 Toll Free  
USA/Canada  
**Europe, Middle East and Africa Technical Support:**  
Phone: 421 33 790 2910  
**Japan Customer Focus Center**  
Phone: 81-3-5773-3850

**ON Semiconductor Website:** [www.onsemi.com](http://www.onsemi.com)  
**Order Literature:** <http://www.onsemi.com/orderlit>

For additional information, please contact your local Sales Representative

NCV4276/D

单击下面可查看定价，库存，交付和生命周期等信息

[>>ON Semiconductor\(安森美\)](#)