

Notification about the transfer of the semiconductor business

The semiconductor business of Panasonic Corporation was transferred on September 1, 2020 to Nuvoton Technology Corporation (hereinafter referred to as "Nuvoton"). Accordingly, Panasonic Semiconductor Solutions Co., Ltd. became under the umbrella of the Nuvoton Group, with the new name of Nuvoton Technology Corporation Japan (hereinafter referred to as "NTCJ").

In accordance with this transfer, semiconductor products will be handled as NTCJ-made products after September 1, 2020. However, such products will be continuously sold through Panasonic Corporation.

Publisher of this Document is NTCJ.

If you would find description "Panasonic" or "Panasonic semiconductor solutions", please replace it with NTCJ.

※ Except below description page

"Request for your special attention and precautions in using the technical information and semiconductors described in this book"

Nuvoton Technology Corporation Japan

□ MN103SD0 Series

Type	MN103SD0Q	MN103SFD0R
Internal ROM type	Mask ROM	FLASH
ROM (byte)	768K	1024K
RAM (byte)	32K	40K
Package (Lead-free)	UBGA257-P-1111A	
Minimum Instruction Execution Time	16.7 ns (at 2.7 V to 3.6 V, 60 MHz)	

■ Interrupts

RESET. IRQ × 11. NMI. Key input. Timer × 32. Input capture × 16. PWM × 6. SIF × 24. I²C × 4. DMA × 18. WDT. A/D. System error

■ Timer Counter

8-bit timer × 8

Reload-down count. Cascade connection possible (usable as a 16-bit to 32-bit timer)

16-bit timer × 6

Up-down count. Input capture. PWM output. Compare/capture register 2 channels

16-bit timer × 6

Reload-down count

Watchdog timer × 1

■ Serial interface

UART/Synchronous interface selective × 10: Serial 0, 1, 3 to A

Start-stop synchronization/Synchronization commonly used (16 bytes containing transmission/reception FIFO): Serial 2

I²C serial interface, multi master transmission/reception function × 2

■ DMA controller

Number of channels: 6 channels

Unit of transfer: 8/16/32 bits

Maximum transfer cycles: 65535

Starting factor: External interrupt. Timer. Input capture. PWM. Serial transmission/reception. I²C transmission/reception. A/D conversion finish. Software

Transfer method: 2-bus cycle transfer

Addressing modes: Fixed. Increment. Decrement

Transfer mode: Word transfer. Burst transfer. Intermittent transfer

■ I/O Pins

I/O 194 : Common use

Input 1 : Exclusive

■ A/D converter

10-bit × 32 channels

■ PWM

12/14-bit resolution × 6 channels

■ ICR

28-bit × 13 channels + 16-bit × 6 channels (common with timer)

■ OCR

16-bit × 12 channels (common with timer)

■ Timer Synchronous Output

4-bit (synchronous output) × 2 channels

■ ROM Correction

8 channels

■ Electrical Characteristics (A/D converter characteristics)

Parameter	Symbol	Condition	Limit			Unit
			min	typ	max	
Resolution					10	Bits
Non-linear error		VDD33 = 3.3 V. VSS = 0.0 V			±3	LSB
A/D conversion time		IOCLK = 20 MHz. T _{AD} = 200 ns	2.4			μs

T_a = 25 °C

Note) T_{AD} is A/D conversion clock cycle

■ Pin Assignment

UBGA257-P-1111A

	A	B	C	D	E	F	G	H	J	K	L	M	N	P	R	T	U	V	W	Y				
20	VDDL	VDDL	PN0, TM20IOA	PM3, SY00T3	PL7, TM7IO	PL4, TM4IO	PL1, SCL0	PK6, KI6	PK2, KI2	PK0, KI0	PJ7, ADM15, A15	PJ5, ADM13, A13	PJ3, ADM11, A11	PJ1, ADM9, A9	PH3, SYSCLK	PH4, DK	PH0, NWE0	PG0, NCS0	VDDB	VDDB	20			
19	VDDL	VDDL	PM7, SY10T3	PM5, SY10T1	PM1, SY00T1	PL6, TM6IO	PL3, TM3IO	PL0, SDA0	PK4, KI4	PK1, KI1	PJ6, ADM14, A14	PJ4, ADM12, A12	PJ2, ADM10, A10	PJ0, ADM8, A8	PH5, AS	PH2, NRE	PG3, NCS3	PG1, NCS1	VDDB	VDDB	19			
18	PN2, TM2IOA	PN1, TM2IOA	VDDL	PM6, SY10T2	PM4, SY10T0	PM0, SY00T0	PL5, TM5IO	PL2	PK5, KI5	PK3, KI3	PJ7, ADM7, A7	PJ5, ADM5, A5	PJ3, ADM3, A3	PJ1, ADM1, A1	PH6, RWSEL	PH1, NWE1	PG2, NCS2	VDDB	PF7, TM2IO	PF6, TM1IO	18			
17	PP0, SBI7	PN4, TM2IOB	PN3, TM2IOB	VDDL	PM2, SY00T2	VSS	VDD18	PK7, KI7	VDD18	VSS	PI6, ADM6, A6	PI4, ADM4, A4	PI2, ADM2, A2	PI0, ADM0, A0	VSS	PG4, NCS4	VDDB	PF5, TM0IO	PF4, IRQ10	PF2, IRQ8	17			
16	PP4, SBO8	PP2, SBI7	PP1, SBO7	PN5, TM2IOB													PF1, IRQ7	PF3, IRQ9	PF0, IRQ6	PE4	16			
15	PP7, SBO9	PP5, SBI8	PP6, SBI9	PP3, SBI8													PE3, NBG	PE5	PE2, NBR	PE0, TM10IO	15			
14	PR2, SBOA	PR0, SBI9	PR1, SBI8	VSS													PD6, D14	PE1, TM1IO	PD7, D15	PD5, D13, IRQ4	14			
13	PS0	PR4, IRQ5	PR5	PR3, SBTA													VSS	PD3, D11, SBI6	PD4, D12, IRQ3	PD2, D10, SBO6	13			
12	PS4, TM14IO	PS2, TM12IO	PS3, TM13IO	PS1													PC7, D7, SBO5	PD1, D9, SBI6	PD0, D8, SBI5	PC6, D6, SBI5	12			
11	PS7	PS5, TM15IO	PS6	VDD33													VDD33	PC4, D4, SBO4	PC5, D5, SBI4	PC3, D3, SBI4	11			
10	P00, AN0	P02, AN2	P04, AN4	P01, AN1														PB5, IRQ0	PC1, D11, SBI3	PC0, D0, SBI3	PC2, D2, SBI3	10		
9	P03, AN3	P05, AN5	P06, AN6	VSS														VSS	PB2, SBI2	PB3, SBO2	PB4, SBI2	9		
8	P07, AN7	P11, AN9	P12, AN10	P10, AN8															PA6, A22	PB0, A24	PA7, A23	PB1, A25	8	
7	P13, AN11	P15, AN13	P17, AN15	P14, AN12															VSS	PA4, A20	PA3, A19	PA5, A21	7	
6	P16, AN14	P20, AN16	P24, AN20	P21, AN17																P96, IRQ1	PA1, A17	PA0, A16	PA2, A18	6
5	P22, AN18	P23, AN19	P26, AN22	VSS	VSS															P85, PWM5	P94, SBO1	P95, SBI1	P97, IRQ2	5
4	P25, AN21	P27, AN23	P30, AN24	VDD33	VSS	VSS	P53, TM23IOB	VDD18	P76, NMI	VOUT	VOUT	VDD18	P71, ICR9	N.C.	VSS	N.C.	VDD33	P90, SBI0	P91, SBO0	P93, SBI1	4			
3	P32, AN26	P31, AN25	VDD33	P34, AN28	P36, AN30	P51, TM24IOA	P56, SDA1	P61, ICR1	P63, ICR3	MMOD	P65, ICR5	P67, ICR7	P73, ICR11	OC _D -SDA	N.C.	N.C.	P82, PWM2	VDD33	P92, SBI0	P84, PWM4	3			
2	VDD33	VDD33	P33, AN27	P35, AN29	P41, WDOVF	P50, TM23IOA	P54, TM24IOB	P57, SCL1	P62, ICR2	VSS	NRST	P66, ICR6	P72, ICR10	N.C.	N.C.	N.C.	P80, PWM0	P83, PWM3	VDD33	VDD33	2			
1	VDD33	VDD33	VREFH	P37, AN31	P40, ADTRG	P52, TM25IOA	P55, TM25IOB	P60, ICR0	LON	OSCI	OSCO	P64, ICR4	P70, ICR8	P74, ICR12	P75	N.C.	OC _D -SCL	P81, PWM1	VDD33	VDD33	1			

Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products. No license is granted in and to any intellectual property right or other right owned by Panasonic Corporation, Nuvoton Technology Corporation Japan or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information de-scribed in this book.
- (3) The products described in this book are intended to be used for general applications (such as office equipment, communications equipment, measuring instruments and household appliances), or for specific applications as expressly stated in this book.
Please consult with our sales staff in advance for information on the following applications, moreover please exchange documents separately on terms of use etc.: Special applications (such as for in-vehicle equipment, airplanes, aerospace, automotive equipment, traffic signaling equipment, combustion equipment, medical equipment and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
Unless exchanging documents on terms of use etc. in advance, it is to be understood that our company shall not be held responsible for any damage incurred as a result of or in connection with your using the products described in this book for any special application.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. We do not guarantee quality for disassembled products or the product re-mounted after removing from the mounting board.
When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) When reselling products described in this book to other companies without our permission and receiving any claim of request from the resale destination, please understand that customers will bear the burden.
- (8) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of our company.

No.070920

单击下面可查看定价，库存，交付和生命周期等信息

[>>Panasonic\(松下\)](#)