

# **General Description**

The WSF60N06A uses advanced trench technology and design to provide excellent RDS(ON) with low gate charge. It can be used in a wide variety of applications.

#### **Features**

- High density cell design for ultra low Rdson
- Fully characterized avalanche voltage and current
- Good stability and uniformity with high E<sub>AS</sub>
- Excellent package for good heat dissipation
- Special process technology for high ESD capability

### **Product Summery**


BVDSS	RDSON	ID	
60V	12mΩ	60A	

# **Application**

- Power switching application
- LED backlighting
- Uninterruptible power supply

### **TO-252 Pin Configuration**





# **Absolute Maximum Ratings**

Symbol	Parameter	Rating	Units	
$V_{DS}$	Drain-Source Voltage	60	V	
$V_{GS}$	Gate-Source Voltage	±20	V	
I <sub>D</sub> @T <sub>C</sub> =25℃	Continuous Drain Current, V <sub>GS</sub> @ 10V <sup>1</sup>	60	Α	
I <sub>D</sub> @T <sub>C</sub> =100℃	Continuous Drain Current, V <sub>GS</sub> @ 10V <sup>1</sup>	41	Α	
I <sub>DM</sub>	Pulsed Drain Current <sup>2</sup>	120	Α	
EAS	Single Pulse Avalanche Energy <sup>3</sup> 290		mJ	
P <sub>D</sub> @T <sub>C</sub> =25℃	Total Power Dissipation⁴ 85		W	
T <sub>J</sub> T <sub>STG</sub>	Operating Junction Temperature Range -55 to 150		$^{\circ}$	

## **Thermal Data**

Symbol	Parameter	Тур.	Max.	Unit
$R_{ heta JA}$	Thermal Resistance Junction-Ambient <sup>1</sup>		62	°C/W
$R_{ heta JC}$	Thermal Resistance Junction-Case <sup>1</sup>		0.57	°C/W

# Electrical Characteristics (T<sub>J</sub>=25 ℃, unless otherwise noted)

Symbol	Parameter	Conditions	Min.	Тур.	Max.	Unit
BV <sub>DSS</sub>	Drain-Source Breakdown Voltage	$V_{GS}$ =0V , $I_D$ =250uA	60			V
$\triangle BV_{DSS}/\triangle T_{J}$	BV <sub>DSS</sub> Temperature Coefficient	Reference to 25℃ , I <sub>D</sub> =1mA		0.057		V/°C
В	Static Drain-Source On-Resistance <sup>2</sup>	V <sub>GS</sub> =10V , I <sub>D</sub> =30A		12	14	mΩ
R <sub>DS(ON)</sub>		V <sub>GS</sub> =4.5V , I <sub>D</sub> =20A		15	20	
$V_{GS(th)}$	Gate Threshold Voltage	\/ -\/   -250uA	2.0	3.0	4.0	V
$\triangle V_{GS(th)}$	V <sub>GS(th)</sub> Temperature Coefficient	$-V_{GS}=V_{DS}$ , $I_D=250uA$		-5.68		mV/℃
	Drain-Source Leakage Current	$V_{DS}$ =48V , $V_{GS}$ =0V , $T_J$ =25 $^{\circ}$ C			1	uA
I <sub>DSS</sub>		V <sub>DS</sub> =48V , V <sub>GS</sub> =0V , T <sub>J</sub> =55℃			5	uA
I <sub>GSS</sub>	Gate-Source Leakage Current	$V_{GS}$ = $\pm 20 V$ , $V_{DS}$ = $0 V$			±100	nA
gfs	Forward Transconductance	V <sub>DS</sub> =5V , I <sub>D</sub> =15A		30		S
$R_g$	Gate Resistance	V <sub>DS</sub> =0V , V <sub>GS</sub> =0V , f=1MHz		1.7	3.4	Ω
$Q_{g}$	Total Gate Charge (4.5V)	V <sub>DS</sub> =30V , V <sub>GS</sub> =4.5V , I <sub>D</sub> =30A		36	45	
$Q_gs$	Gate-Source Charge			9.9	18	nC
$Q_{gd}$	Gate-Drain Charge			6.6	15	
T <sub>d(on)</sub>	Turn-On Delay Time	$V_{DS}$ =30V , $V_{GS}$ =10V , $I_{D}$ =2A , R=1 $\Omega$ .		12	14.4	
Tr	Rise Time			5.2	10	
T <sub>d(off)</sub>	Turn-Off Delay Time			38	55	ns
T <sub>f</sub>	Fall Time			27	32	
C <sub>iss</sub>	Input Capacitance	V <sub>DS</sub> =25V , V <sub>GS</sub> =0V , f=1MHz		2498		
C <sub>oss</sub>	Output Capacitance			185		pF
C <sub>rss</sub>	Reverse Transfer Capacitance			80		

### **Diode Characteristics**


Symbol	Parameter	Conditions	Min.	Тур.	Max.	Unit
Is	Continuous Source Current <sup>1,6</sup>	V <sub>G</sub> =V <sub>D</sub> =0V , Force Current			38	Α
I <sub>SM</sub>	Pulsed Source Current <sup>2,6</sup>				90	Α
$V_{SD}$	Diode Forward Voltage <sup>2</sup>	V <sub>GS</sub> =0V , I <sub>S</sub> =1A , T <sub>J</sub> =25℃			1.2	V
t <sub>rr</sub>	Reverse Recovery Time	- IF=1A ,dl/dt=100A/μs,TJ=25 C		35		nS
Q <sub>rr</sub>	Reverse Recovery Charge			47		nC

### Notes:


- 1. Repetitive Rating: Pulse width limited by maximum junction temperature.
- 2. Surface Mounted on FR4 Board, t ≤ 10 sec.
- **3.** Pulse Test: Pulse Width ≤  $300\mu$ s, Duty Cycle ≤ 2%.
- 4. Guaranteed by design, not subject to production
- **5.** E<sub>AS</sub> condition: Tj=25  $^{\circ}$ C,V<sub>DD</sub>=30V,V<sub>G</sub>=10V,L=0.5mH,Rg=25



## **Typical Characteristics**



**Figure 1 Output Characteristics** 



**Figure 2 Transfer Characteristics** 




Figure 3 Rdson- Drain Current




Figure 4 Rdson-JunctionTemperature




Figure 5 Gate Charge




Figure 6 Source- Drain Diode Forward




Figure 7 Capacitance vs Vds




Figure 9 Power De-rating




Figure 8 Safe Operation Area





Figure 10 ID Current- JunctionTemperature



**Figure 11 Normalized Maximum Transient Thermal Impedance** 



#### **Attention**

- 1, Any and all Winsok power products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your Winsok power representative nearest you before using any Winsok power products described or contained herein in such applications.
- 2, Winsok power assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all Winsok power products described or contained herein.
- 3, Specifications of any and all Winsok power products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- 4, Winsok power Semiconductor CO., LTD. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- 5,In the event that any or all Winsok power products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- 6, No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of Winsok power Semiconductor CO., LTD.
- 7, Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. Winsok power believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.
- 8, Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the Winsok power product that you Intend to use.
- 9, this catalog provides information as of Sep.2014. Specifications and information herein are subject to change without notice.

单击下面可查看定价,库存,交付和生命周期等信息

>>WINSOK(微硕)