

General Description

WSF80N06 use advanced VD MOST technology to provide low RDS(ON), low gate charge, fast switching. This device is specially designed to get better ruggedness and suitable to use in

Low RDS(on) & FOM
 Extremely low switching loss
 Excellent stability and uniformity or Invertors


Applications

Consumer electronic power supply Motor control
 Synchronous-rectification Isolated DC
 Synchronous-rectification applications

Product Summary

BVDSS	RDS(ON)	ID
60V	7.2mΩ	80A

TO-252 Pin Configuration



Absolute Maximum Ratings@Tj=25°C(unless otherwise specified)

Symbol	Parameter	Rating	Units
V _{DS}	Drain-Source Voltage	60	V
V _{GS}	Gate-Source Voltage	±20	V
I _D @T _C =25°C	Continuous Drain Current, V _{GS} @ 10V	80	A
I _D @T _C =100°C	Continuous Drain Current, V _{GS} @ 10V	43	A
I _{DM}	Pulsed Drain Current	270	A
P _D @T _C =25°C	Total Power Dissipation	104	W
T _{STG}	Storage Temperature Range	-55 to 150	°C
T _J	Operating Junction Temperature Range	-55 to 150	°C

Thermal Data

Symbol	Parameter	Typ.	Max.	Unit
R _{θJA}	Thermal Resistance Junction-Ambient	---	62.5	°C/W
R _{θJC}	Thermal Resistance Junction-Case	---	1.2	°C/W

Electrical Characteristics (T_J=25 °C, unless otherwise noted)

Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
BVDSS	Drain-Source Breakdown Voltage	V _{GS} =0V , I _D =250uA	60	---	---	V
RDS(ON)	Static Drain-Source On-Resistance	V _{GS} =10V , I _D =45A	---	7.2	12	mΩ
		V _{GS} =10V , I _D =30A	---	8.3	15	
VGS(th)	Gate Threshold Voltage	V _{GS} =V _{DS} , I _D =250uA	1	1.4	3	V
IDSS	Drain-Source Leakage Current	V _{DS} =60V , V _{GS} =0V , T _J =25°C	---	---	10	uA
		V _{DS} =48V , V _{GS} =0V , T _J =125°C	---	---	250	
IGSS	Gate-Source Leakage Current	V _{GS} =±20V , V _{DS} =0V	---	---	±100	nA
Qg	Total Gate Charge	I _D =30A	---	33	45	nC
Qgs	Gate-Source Charge	V _{DS} =48V	---	5	---	
Qgd	Gate-Drain Charge	V _{GS} =4.5V	---	21	---	
Td(on)	Turn-On Delay Time	V _{DS} =30V I _D =30A	---	10	---	ns
T _r	T _{Rise} ime	R _G =3.3Ω	---	43	---	
Td(off)	Turn-Off Delay Time	V _{GS} =10V	---	47	---	
T _f	T _{Fall} ime		---	80	---	
Ciss	Input Capacitance	V _{GS} =0V	---	2680	3300	pF
Coss	Output Capacitance	V _{DS} =25V	---	260	---	
C _{rSS}	Reverse Transfer Capacitance	f=1.0MHz	---	180	---	

Diode Characteristics

Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
VSD	Diode Forward Voltage	V _{GS} =0V , I _S =45A , T _J =25°C	---	---	1.3	V
t _{rr}	Reverse Recovery Time	I _F =10A , dI/dt=100A/μs, T _J =25°C	---	30	---	nS
Q _{rr}	Reverse Recovery Charge		---	18	---	nC

Typical Characteristics




Fig 1. Typical Output Characteristics




Fig 2. Typical Output Characteristics




Fig 3. On-Resistance v.s. Gate Voltage




Fig 4. Normalized On-Resistance v.s. Junction Temperature




Fig 5. Forward Characteristic of Reverse Diode




Fig 6. Gate Threshold Voltage v.s. Junction Temperature




Fig 7. Gate Charge Characteristics




Fig 8. Typical Capacitance Characteristics




Fig 9. Maximum Safe Operating Area




Fig 10. Effective Transient Thermal Impedance




Fig 11. Transfer Characteristics




Fig 12. Gate Charge Waveform

Attention

- 1, Any and all Winsok power products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your Winsok power representative nearest you before using any Winsok power products described or contained herein in such applications.
- 2, Winsok power assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all Winsok power products described or contained herein.
- 3, Specifications of any and all Winsok power products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- 4, Winsok power Semiconductor CO., LTD. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- 5, In the event that any or all Winsok power products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- 6, No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of Winsok power Semiconductor CO., LTD.
- 7, Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. Winsok power believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.
- 8, Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the Winsok power product that you intend to use.
- 9, this catalog provides information as of Sep. 2014. Specifications and information herein are subject to change without notice.

单击下面可查看定价，库存，交付和生命周期等信息

[>>WINSOK\(微硕\)](#)