


PNP Silicon Epitaxial Transistor

for switching and amplifier applications



Absolute Maximum Ratings (Ta = 25°C)

Parameter	Symbol	Value	Unit
Collector Base Voltage	V_{CBO}	BC856	-80
		BC857, BC860	-50
		BC858, BC859	-30
Collector Emitter Voltage	V_{CEO}	BC856	-65
		BC857, BC860	-45
		BC858, BC859	-30
Emitter Base Voltage	V_{EBO}	-5	V
Collector Current	I_C	-100	mA
Peak Collector Current	I_{CM}	-200	mA
Power Dissipation	P_{tot}	200	mW
Junction Temperature	T_j	150	°C
Storage Temperature Range	T_{Stg}	- 65 to + 150	°C

hFE Classification

TYPE	BC856A	BC856B	BC856C	BC857A	BC857B	BC857C	BC858A	BC858B	BC858C
MARKING	3A	3B	3C	3E	3F	3G	3J	3K	3L
Range	110~220	200~450	420~800	110~220	200~450	420~800	110~220	200~450	420~800
TYPE	BC859A	BC859B	BC859C	BC860A	BC860B	BC860C			
MARKING	4A	4B	4C	4E	4F	4G			
Range	110~220	200~450	420~800	110~220	200~450	420~800			

Characteristics at Ta = 25°C

Characteristics		Symbols	Min	Max	Units	
DC Current Gain at $-V_{CE} = 5\text{ V}$, $-I_C = 2\text{ mA}$	Current Gain Group	A	h_{FE}	110	220	V
		B	h_{FE}	200	450	
		C	h_{FE}	420	800	
Collector Base Cutoff Current at $-V_{CB} = 30\text{ V}$		I_{CBO}	-	-15	nA	
Collector Base Breakdown Voltage at $-I_C = 10\text{ }\mu\text{A}$	BC856	$V_{(BR)CBO}$	-80		V	
	BC857, BC860		-50			
	BC858, BC859		-30			
Collector Emitter Breakdown Voltage at $-I_C = 10\text{ }\mu\text{A}$	BC856	$V_{(BR)CES}$	-80		V	
	BC857, BC860		-50			
	BC858, BC859		-30			
Collector Emitter Breakdown Voltage at $-I_C = 10\text{ mA}$	BC856	$V_{(BR)CEO}$	-65		V	
	BC857, BC860		-45			
	BC858, BC859		-30			
Emitter Base Breakdown Voltage at $-I_E = 1\text{ }\mu\text{A}$		$V_{(BR)EBO}$	-5		V	
Collector Emitter Saturation Voltage at $-I_C = 10\text{ mA}$, $-I_B = 0.5\text{ mA}$ at $-I_C = 100\text{ mA}$, $-I_B = 5\text{ mA}$		$V_{CE(sat)}$		-0.3	V	
						-0.65
Base Emitter On Voltage at $-I_C = 2\text{ mA}$, $-V_{CE} = 5\text{ V}$ at $-I_C = 10\text{ mA}$, $-V_{CE} = 5\text{ V}$		$V_{BE(on)}$	-0.6	-0.75	V	
				-		-0.82
Current Gain Bandwidth Product at $-V_{CE} = 5\text{ V}$, $-I_C = 10\text{ mA}$, $f = 100\text{ MHz}$		f_T	100		MHz	
Current Gain Bandwidth Product at $-V_{CE} = 5\text{ V}$, $-I_C = 10\text{ mA}$, $f = 100\text{ MHz}$		C_{ob}		6	pF	
Noise Figure at $-I_C = 200\text{ }\mu\text{A}$, $-V_{CE} = 5\text{ V}$, $R_G = 2\text{ K}\Omega$, $f = 1\text{ KHz}$ at $-I_C = 200\text{ }\mu\text{A}$, $-V_{CE} = 5\text{ V}$, $R_G = 2\text{ K}\Omega$, $f = 30\text{ ~}15\text{ KHz}$	BC856, BC857, BC858	NF		10	dB	
	BC859, BC860			4		
	BC859			4		
	BC860			2		

Typical Characteristics




Figure 1. Static Characteristic




Figure 2. DC current Gain




Figure 3. Base-Emitter Saturation Voltage
Collector-Emitter Saturation Voltage




Figure 4. Base-Emitter On Voltage




Figure 5. Collector Output Capacitance




Figure 6. Current Gain Bandwidth Product

Ordering information


Package	Packing Description	Base Quantity	Packing Quantity
SOT-23	Tape/Reel, 7" reel	3000pcs/Reel	24000PCS/Box 120000PCS/Carton

Package Dimensions

SOT-23

Dim.	Millimeter (mm)		mil	
	Min.	Max.	Min.	Max.
A	0.9	1.15	35	45
A1	0.1		3.9	
bp	0.38	0.48	15	19
C	0.09	0.15	3.54	5.9
D	2.8	3.0	110	118
E	1.2	1.4	47	55
E	1.9		75	
E1	0.95		37	
HE	2.1	2.55	83	100
Lp	0.15	0.45	5.9	18
Q	0.45	0.55	18	22
v	0.2		7.9	
W	0.1		4	

The recommended mounting pad size



Disclaimer

The information presented in this document is for reference only. GuangDong Youfeng Microelectronics Co.,Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise. The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices),YFW or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale. This publication supersedes & replaces all information previously supplied. For additional information, please visit our website <https://www.yfwdiode.com>, or consult YFW sales office for further assistance.

单击下面可查看定价，库存，交付和生命周期等信息

[>>YFW\(佑风微\)](#)