

KEMET, Z-SMS, Ferrite Beads, Noise Suppression, 200 mOhms



| Dimensions | |
|------------|-----------------|
| Chip Size | 0603 |
| L | 1.6mm +/-0.15mm |
| W | 0.8mm +/-0.15mm |
| T | 0.8mm +/-0.15mm |
| B | 0.3mm +/-0.2mm |

| Packaging Specifications | |
|--------------------------|------|
| Packaging: | T&R |
| Packaging Quantity: | 4000 |

| General Information | |
|---------------------|--|
| Series: | Z-SMS |
| Style: | SMD Chip |
| Description: | Chip Bead Signal Line |
| Features: | Designed As A Noise Countermeasure For 200MHz-500MHz Range Where The Rise Of The Z Component Is In The High Frequency Area |
| RoHS: | Yes |

| Specifications | |
|----------------------|-------------------|
| Impedance: | 30 Ohms (100 mHz) |
| Impedance Tolerance: | 25% |
| Ripple Current: | 500 mA (MAX) |
| Temperature Range: | -55/+125°C |
| Resistance: | 0.2 Ohms |

单击下面可查看定价，库存，交付和生命周期等信息

[>>KEMET Electronics\(基美\)](#)