


KEMET, Z-SMS, Ferrite Beads, Noise Suppression, 600 mOhms



| General Information | |
|---------------------|---|
| Series: | Z-SMS |
| Style: | SMD Chip |
| Description: | Chip Bead Signal Line |
| Features: | The Best Material In The Z-SMS Series To Suppress The XL Component And Stop The Reduction Of The Wave-Form Integrity While Maintaining Attenuation In The High Frequency Area |
| RoHS: | Yes |

| Dimensions | |
|------------------|-----------------|
| Chip Size | 0402 |
| L | 1mm +/-0.05mm |
| W | 0.5mm +/-0.05mm |
| T | 0.5mm +/-0.05mm |
| B | 0.25mm +/-0.1mm |

| Specifications | |
|-----------------------------|--------------------|
| Impedance: | 600 Ohms (100 mHz) |
| Impedance Tolerance: | 25% |
| Ripple Current: | 300 mA (MAX) |
| Temperature Range: | -55/+125°C |
| Resistance: | 0.6 Ohms |

| Packaging Specifications | |
|----------------------------|-------|
| Packaging: | T&R |
| Packaging Quantity: | 10000 |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

单击下面可查看定价，库存，交付和生命周期等信息

[>>KEMET Electronics\(基美\)](#)