


## SE-400 SERIES

## **Ground-Fault-Relay Test Unit**



### **Simplified Circuit Diagram**



#### **Description**

The SE-400 is a ground-fault-relay test unit designed to test current pickup level, time delay and coordination of groundfault protection.

The tester injects current through the window of installed ground-fault current transformers to verify the operation of ground-fault monitors and relays.

It is used on substations, motor control centers (MCCs), central distribution panels, switchboards, and test benches to verify relay operation.

The SE-400 tests the entire ground-fault circuit including current transformers, wiring, ground-fault relay and the operation of the interrupting device. It is recommended to test every relay and its current interrupting device annually.

#### **Features & Benefits**

| FEATURES                             | BENEFITS   |  |
|--------------------------------------|--|--|
| Adjustable Current<br>Setpoint       | Current range is 0.5 to 9.9 A                        |  |
| Adjustable Time<br>Duration Setpoint | Duration range is 0.1 to 9.9 s, or continuous output |  |
| Small Form Factor                    | Lightweight and compact for portability              |  |
| Remote Test Input                    | Allows test to be initiated from another location    |  |

### **Ordering Information**

| ORDERING NUMBER | CONTROL POWER |
|-----------------|---------------|
| SE-400          | 120 Vac       |

#### **Specifications**

Input Voltage 84-134 Vac, 50/60 Hz, 80 VA **Dimensions H** 219 mm (8.6"):

**W** 99 mm (3.9"); **D** 143 mm (5.6") 0.5-9.9 A

**Output Current Settings Output Duration Settings** 0.1-9.9 s or continuous **Output Voltage** 5.0 Vac maximum **Conformally Coated** Standard feature Warranty

5 Year Mounting Surface, Panel

Rev: 4-A-081515

Based on Manual Rev: 1-A-072115

## 单击下面可查看定价,库存,交付和生命周期等信息

# >>Littelfuse(美国力特)