# Part Numbering

## CERAFIL® for FM

(Part Number) SF E LF 10M7 F A A0 -B0

#### 1 Product ID

Product ID	
SF	Ceramic Filters

#### 20scillation/Number of Elements

Code	Oscillation/Number of Elements	
E	2 Elements Thickness Expander mode	
Т	3 Elements Thickness Expander mode	
V	2 Elements Thickness Expander mode (2nd Harmonic)	
ĸ	2 Elements Thickness Expander mode (3rd Over Tone)	

## 3Structure/Size

Code	Structure/Size
L	Lead Type
C	Chip Type

 $<sup>\</sup>hfill \square$  is expressed "A" or subsequent code, which indicates the structure/size.

# **4** Nominal Center Frequency

Expressed by four-digit alphanumerics. The unit is in hertz (Hz). Decimal point is expressed by capital letter "M" in case of MHz.

#### **5**3dB Bandwidth

<u> </u>	
Code	3dB Bandwidth
С	450kHz min
D	350kHz min
E	330kHz
F	280kHz
G	230kHz
Н	180kHz
J	150kHz
К	110kHz
L	80kHz
М	50kHz
N	35kHz

## **6**Center Frequency/Tolerance

Code	Center Frequency	Tolerance
Α	Center Frequency mentioned by specification	±30kHz
В	-30kHz shifted from center frequency of code "A"	±30kHz
С	+30kHz shifted from center frequency of code "A"	±30kHz
D	-60kHz shifted from center frequency of code "A"	±30kHz
E	+60kHz shifted from center frequency of code "A"	±30kHz
Н	Center Frequency mentioned by specification ±	
٧	-50kHz shifted from center frequency of code "H" ±25	
W	+50kHz shifted from center frequency of code "H"	±25kHz
K	Center Frequency mentioned by specification	±20kHz
Z	Combination of A, B, C, D, E	_
М	Combination of A, B, C	-
F	Nominal Center Frequency	_

3dB bandwidth of "F" signifies the frequency difference (both + and -) from reference frequency which is nominal center frequency.

#### Series

Code	Series
A0	Two-digit alphanumerics express series

#### 8 Packaging

Code	Packaging	
-B0	Bulk	
-R0	Embossed Taping ø180mm	
-R1	Embossed Taping ø330mm	
-A0	1500pcs. /Radial Taping H <sub>0</sub> =18mm	
-A1	1000pcs. /Radial Taping H₀=18mm	

Radial taping is applied to lead type and embossed taping to chip type. With non-standard products, two-digit alphanumerics indicating "Individual Specification" are added between "Series" and "Series".

# 单击下面可查看定价,库存,交付和生命周期等信息

>>Murata(村田)