

Capacitors 2018




KYOCERA Corporation





citors	
How to Order	1
Dimensions etc.	2
General CM Series	3 - 5
Low Profile CT Series	6
High-Q CU Series	6
Au Termination AT Series	7
Soft Termination ST Series	7
High Voltage CF Series	8
Three Terminal Capacitors KNH Series	9
Test Conditions and Standards	10 – 13
Packaging	14 – 15
Precautions	16 – 19
Part Number List	20 – 25
Notes for Using the Catalog	26
Design Tool Introduction	26





RoHS Compliant

■Features

- Kyocera's series of Multilayer Ceramic Chip Capacitors are designed to meet a wide variety of needs. We offer a complete range of products for both general and specialized applications.
- We have a network worldwide in order to supply our global customer bases quickly and efficiently and to maintain our reputation as one of the highest-volume producers in the industry
- All our products are highly reliable due to their monolithic structure of high-purity and superfine uniform ceramics and their integral internal electrodes.
- By combining superior manufacturing technology and materials with high dielectric constants, we produce extremely compact components with exceptional specifications.
- Our stringent quality control in every phase of production from material procurement to shipping ensures consistent manufacturing and super quality.
- Kyocera components are available in a wide choice of dimensions, temperature characteristics, rated voltages, and terminations to meet specific configurational requirements.

■KYOCERA PART NUMBER

Above digits are used to track individual ** *BPackaging specification or thickness.

(Example)
①Series : CM Series(General)
②Size : 0201
③Dielectric : X5R

® Packaging : Cavity pitch 2mm / Reel Size ∮ 180

1) SERIES CODE

CODE	Туре
CM	General
СТ	Low Profile
CU	High-Q
АТ	Au Termination
ST	Soft Termination
CF	High-Voltage
KNH	Three Terminal Capacitors

②Size Code

E DIZC OUCC						
CODE	EIA	JIS				
02	01005	0402				
03	0201	0603				
05	0402	1005				
105	0603	1608				
21	0805	2012				
316	1206	3216				
32	1210	3225				
42	1808	4520				
43	1812	4532				

6 VOLTAGE CODE

CODE Rated Voltage

4Vdc 6.3Vdc

10Vdc

16Vdc

25Vdc

35Vdc

50Vdc

100Vdc

250Vdc

630Vdc 1000Vdc

2000Vdc

04

06 10

16

25

35

50

100

250

630

1000

3DIELECTRIC CODE

_							
Te	Temperature Compensation Type						
CODE	Temperature Range (°C)	ppm	n/℃				
CG	-55 to 125	0	±30				
CH	55 to 125	U	±60				

- · All parts of COG will be marked as "CG" but will conform to the above table.
- Temperature coefficients are determined by calculation based on measurement at 20°C and 85°C.

	High Dielectric Constant Type							
CODE	Temperature Range (°C)	△C max. (%)	Standard Temperature (°C)					
X5R	-55 to 85	± 15						
X7R	-55 to 125	± 15	25					
X7S	55 (0 125	±22						

4CAPACITANCE CODE

Capacitance expressed in pF.
Two significant digits plus number of zeros.
For Values < 10pF, Letter R denotes decimal point, < 1,000pF = 1nF, 1,000nF = 1µF)

(Example)

CODE	Capacitance				
R50	0.5pF				
1R0	1pF				
100	10pF				
101	100pF				
102	1nF				
103	10nF				
104	100nF				
105	1µF				
106	10µF				

	L OTANDAND NOMBER					
E3	E6	E12 E24				
	1.0	1.0	1.0	1.1		
1.0	1.0	1.2	1.2	1.3		
1.0	1.5	1.5	1.5	1.6		
	1.5	1.8	1.8	2.0		
2.	2.2	2.2	2.2	2.4		
2.2	2.2	2.7	2.7	3.0		
2.2	3.3	3.3	3.3	3.6		
	5.5	3.9	3.9 4.3			
	4.7	4.7	7 4.7 5.			
4.7	4.7	5.6	5.6	6.2		
	6.8	6.8	6.8	7.5		
	0.0	8.2	8.2	9.1		

E STANDARD NUMBER

⑤TOLERANCE CODE

Temperature Compensation Type (COG)						
CODE	Tolerance					
A*	±0.05pF					
В	±0.1pF					
С	±0.25pF					
D	±0.5pF					
G*	±2%					
J	±5%					
K	± 10%					

^{*:} Option

High Dielectric Constant Type(X5R/X7R/X7S)					
CODE	Tolerance				
J*	±5%				
K	± 10%				
М	±20%				

^{* :} Option

(7) TERMINATION CODE

CODE	Termination					
Α	Nickel Barrier/ Tin					
G*1	Nickel Barrier/ Au					
K*2	Nickel Barrier/ Au					
Y*	Nickel Barrier/ Cu					
S	Nickel Barrier/ Tin (Soft Termination)					


- * :Option
- *1: AuSn solder and conductive adhesive.
- *2: Wire bonding and conductive adhesive.

®PACKAGING CODE


CODE	Size Code	Cavity pitch	Reel size
Т	43	8mm	
'	105 to 42	4mm	
Н	02 to 05 2mm φ 180		Φ 180
Q	03/05	1mm	
Р	02	1mm	
L	105 to 32	4mm	
N	02 to 05	2mm	φ330
W	03/05	1mm	



■Dimension




■Packaging Code




Size	Co	de	Dimension	Dimension (mm)						Maximum qua	ntity per reel
Size	EIA	JIS	Code	L	W	Т	P min.	P max.	P to P min.	φ 180Reel	φ 330Reel
02	01005	0402	Α	0.4±0.02	0.2±0.02	0.2±0.02	0.07	0.14	0.13	40kp (E4/1) 20kp (P8/2)	80kp (P8/2)
			Α	0.6±0.03	0.3±0.03	0.22 max.	0.10	0.20	0.20	30kp (P8/1)	150kp(P8/1)
			В	0.0 ± 0.03	0.5 ± 0.05	0.3±0.03	0.10	0.20	0.20	15kp (P8/2)	50kp (P8/2)
03	0201	0603	С	0.6 ± 0.05	0.3±0.05	0.3±0.05	0.13	0.23	0.19	30kp (P8/1) 15kp (P8/2)	150kp(P8/1) 50kp(P8/2)
			D E	0.6±0.09	0.3±0.09	0.25 max. 0.3±0.09	0.13	0.23	0.19	15kp (P8/2)	_
			F	0.6±0.10	0.3±0.10	0.3±0.10					
			Α			0.22 max.				20kp(P8/1)	100kp (P8/1)
			В	1.0 ± 0.05	0.5±0.05	0.33 max.	0.15	0.35	0.30	10kp (P8/2)	50kp (P8/2)
			С			0.5±0.05					
05	0402	1005	D	1.0±0.07	0.5±0.07	0.5±0.07	0.15	0.35	0.30	20kp (P8/1)	_
			E	1.0±0.10	0.5±0.10	0.5±0.10				10kp (P8/2)	50kp (P8/2)
			F*	1.0±0.10	0.5±0.20	0.50 max	0.05	0.25	_	10kp (P8/2)	_
			G	1.0±0.15	0.5±0.15	0.5±0.15	0.15	0.35	0.30	20kp (P8/1) 10kp (P8/2)	50kp (P8/2)
			H	1.0±0.20	0.5±0.20	0.33 max.	0.15	0.35	0.35 0.30	10kp (P8/2) -	
			K* 0.5±0.20 0.5±0.20	0.5±0.20	0.05	0.25 —	TUKP (FO/ Z)				
	0603 16	0603 1608	Α			0.55 max.		0.20			
105			В	1.6±0.10	0.8±0.10	0.8±0.10	0.20	0.60	0.50	4kp (P8/4)	10kp (P8/4)
			С	1.6 ± 0.15	0.8±0.15	0.8±0.15					
	0005		A B	001010	1.25±0.10	0.95 max. 0.85±0.10	0.20	0.75	0.70	4kp (P8/4)	10kp (P8/4)
0.1			0005	0040	C D	2.0 ± 0.10	1.25±0.10 1.05±0.10 0.20 0.75 0.70	0.70	3kp (E8/4)	10kp (E8/4)	
21	0805	2012	E	2.0±0.15	1.25±0.15	0.95 max. 1.25±0.15	0.20			4kp (P8/4) 3kp (E8/4)	10kp (P8/4) 10kp (E8/4)
			G H	2.0±0.20	1.25±0.20	0.95 max. 1.25±0.20		0.20	0.75	0.70	4kp (P8/4) 3kp (E8/4)
			A B	3.2±0.20	1.6±0.15	1.15±0.10 1.25±0.10	0.30	0.85	1.40	3kp (E8/4)	10kp (E8/4)
316	1206	3216	C	3.2 - 0.20	1.0 ± 0.15	1.6±0.15	6±0.15	1.40	2.5kp(E8/4)	5kp(E8/4)	
0.0	1200	02.0	D	3.2±0.20	1.6 ± 0.20	1.6 ± 0.20		0.85	1.40	2.5kp (E8/4)	5kp (E8/4)
			F	3.2±0.30	1.6±0.30	1.6±0.30	0.30	0.85	1.90	2kp (E8/4)	_
00	1010	0005	A	001000	051000	1.6±0.15	0.00	100	1 10	2.5kp (E8/4)	5kp (E8/4)
32	1210	210 3225	B C	3.2 ± 0.30	2.5±0.20	2.0±0.20 2.5±0.20	0.30	1.00	1.40	2kp (E8/4) 1kp (E8/4)	5kp (E8/4) 4kp (E8/4)
42	1808	4520	A	4.5±0.20	2.0±0.20	2.5 ± 0.20 2.2 max.	0.15	0.85	2.60	2kp(E12/4)	4NP(E0/4)
43	1812	4532	A	4.5±0.30	3.2±0.20	2.5 max.	0.30	1.10	2.00	0.5kp (E12/8)	_

^{*:} KNH Series

■Structure





- · Please contact your local Kyocera sales office or distributor for specifications not covered in this catalog.
- Our products are continually being improved. As a result, the capacitance range of each series is subject to change without notice. Please contact an sales representative to confirm compatibility with your application.



General

CM Series

[RoHS Compliant Products]

■Features

We offer a diverse product line ranging from ultra-compact (0.4 $\!\times$ 0.2mm) to large (3.2×2.5mm) components configured for a variety of temperature characteristics, rated voltages, and packages. We offer the choice and flexibility for almost any applications.

■ Applications

This standard type is ideal for use in a wide range of applications, from commercial to industrial equipment.

Temperature Compensation Dielectric

Part Number List: P20

Capacitance chart

	ze Code)		102 005)			M0 020		CM05 (0402)	CM10 (0603)5 3)
	tage (Vdc) ance (pF)	16	2!	5		50		50	50	
1R0 1R5	1.0 1.5									
	2.0									
	3.0 4.0									
	5.0 6.0									
	7.0		А							
	8.0 9.0									
100 120	10					_				
120	12 15					В				
	18 22						L			
	27			•						
	33 39									
	47	Α								
	56 68	_ ^ _					H			_
	82									
101 121	100 120				\vdash		_			-
	150 180	A								
	220							С		_
	270 330									
	390									_
	470 560									
	680 820								В	
102	1000									

· E12 Series

Please contact for capacitance value other than standard.

: Optional Spec.

Please refer to the below table for detail. In case of "B" for CM03; L: 0.6±0.03mm W: 0.3±0.03mm T: 0.3±0.03mm

Alphabets in capacitance chart denote dimensions.

Size	Size Code	Dir	nension (m	n)
SIZE	Code	L	W	Т
02	Α	0.4±0.02	0.2±0.02	0.2±0.02
03	В	0.6±0.03	0.3±0.03	0.3±0.03
05	С	1.0±0.05	0.5±0.05	0.5±0.05
105	В	1.6±0.10	0.8±0.10	0.8±0.10



General

CM Series

[RoHS Compliant Products]

X5R Dielectric Capacitance chart

Part Number List: P21-23

(EIA	Size Code)		102 005)			CM03 (0201)					CN (04	105 02)				CM (06	105 03)	
Capac	/oltage (Vdc) itance (pF)	6.3	16	4	6.3	10	16	25	4	6.3	10	16	25	35	6.3	10	16	25
101	100																	
151	150 220 330																	
102	470 680 1000		A8					В3										
152	1500 2200 3300																	
103	4700 6800 10000																	
153	15000 22000 33000	A8																
104	47000 68000 100000					B7							C3					
105	220000 470000 1000000	A8			B8]		E10]			C7	C8 C7	C8	[C7]	[C7]				C8
106	2200000 4700000 10000000			[E8]	[C8/E8]	[E9]				C8 G8 J8	C8	[J8]			C5 C8	C8	B8	
	15000000 22000000								G8 }									

	Size CM21 (0805)				CM316 (1206)						CM32 (1210)						
Capaci	/oltage (Vdc) itance (pF)	6.3	10	16	25	50	6.3	10	16	25	50	100	6.3	10	16	25	50
105	1000000				D3	D8											
106	2200000 4700000 10000000	H5	D4	D3 F8 H8	H8			C4	C3	C3 D8	D3]	D3]				C3 C8	C3
	22000000 47000000						D5		D8				C5	C4	CS	C8	

⟨Standard Capacitance Value⟩

Capacitance value of less than 0.1µF: E6 Series
Capacitance value of 0.1µF and larger: E3 Series
Places contact for capacitance value other than at-

Please contact for capacitance value other than standard.

Optional Spec.

Two digits alphanumerics in capacitance chart denote dimensions and tan δ . Please refer to the below table for detail.

(Example)

In case of "B3" for CM03;

L: 0.6 ± 0.03 mm W: 0.3 ± 0.03 mm T: 0.3 ± 0.03 mm Tan δ : 5.0% max.

Size	Size	Dir	mension (m	m)
Size	Code	L	W	Т
02	Α	0.4±0.02	0.2±0.02	0.2±0.02
	В	0.6±0.03	0.3±0.03	0.3±0.03
03	С	0.6±0.05	0.3±0.05	0.3±0.05
	Е	0.6±0.09	0.3±0.09	0.3±0.09
	С	1.0±0.05	0.5±0.05	0.5±0.05
05	G	1.0±0.15	0.5±0.15	0.5±0.15
	J	1.0±0.20	0.5±0.20	0.5±0.20
105	В	1.6±0.10	0.8±0.10	0.8±0.10
105	С	1.6±0.15	0.8±0.15	0.8±0.15
	D	2.0±0.10	1.25±0.10	1.25±0.10
21	F	2.0±0.15	1.25±0.15	1.25±0.15
	Н	2.0±0.20	1.25±0.20	1.25±0.20
316	С	3.2±0.20	1.6±0.15	1.6±0.15
310	D	3.2±0.20	1.6±0.20	1.6±0.20
32	С	3.2±0.30	2.5±0.20	2.5±0.20

Tan δ Code	Tan δ
3	5.0%max.
4	7.0%max.
5	7.5%max.
7	10.0%max
8	12.5%max
9	15.0%max
10	20.0%max





General

CM Series

[RoHS Compliant Products]

X7R Dielectric Part Number List: P21-23

Capacitance chart

	Size Code)	CM02 (01005)		CM03 (0201)		CM05 (0402)		CM105 (0603)				CM21 (0805)		
	/oltage(Vdc) itance (pF)	16	10	16	25	25	6.3	10	16	6.3	10	16	25	50
101 151	100 150 220 330				B2									
102 152	470 680 1000 1500	A8		B2										
152	2200 3300 4700		— вз —											
103 153	6800 10000 15000													
153	22000 33000													
104	47000 68000 100000					C8								
105	220000 470000 1000000							B8	B8		D3		D8	[H3]
106	2200000 4700000 10000000						C8			H8	[H8]	H8	H8	

Size (EIA Code)			CM316 (1206)			CM32 (1210)			
Rated Voltage(Vdc) Capacitance (pF)	6.3	10	16	25	50	16	25	50	
2200000 4700000 106 10000000			D8	D8 D3	[D3]	C2	C8	C3	
22000000	D8	D5				C8			

(Standard Capacitance Value)

Capacitance value of less than 0.1µF: E6 Series Capacitance value of 0.1µF and larger: E3 Series

Please contact for capacitance value other than standard.

Optional Spec.

Two digits alphanumerics in capacitance chart denote dimensions and tan δ . Please refer to the below table for detail.

(Example)

In case of "B3" for CM03;

L: 0.6 ± 0.03 mm W: 0.3 ± 0.03 mm T: 0.3 ± 0.03 mm Tan δ : 5.0% max.

Size	Size	Dir	nension (mi	m)
Size	Code	L	W	Т
02	Α	0.4±0.02	0.2±0.02	0.2±0.02
03	В	0.6±0.03	0.3±0.03	0.3±0.03
05	С	1.0±0.05	0.5±0.05	0.5±0.05
105	В	1.6±0.10	0.8±0.10	0.8±0.10
105	С	1.6±0.15	0.8±0.15	0.8±0.15
21	D	2.0±0.10	1.25±0.10	1.25±0.10
21	Н	2.0±0.20	1.25±0.20	1.25±0.20
316	D	3.2±0.20	1.6±0.20	1.6±0.20
32	С	3.2±0.30	2.5±0.20	2.5±0.20

Tan δ Code	Tan δ
2	3.5%max.
3	5.0%max.
5	7.5%max.
8	12.5%max.

X7S Dielectric

Part Number List: P22

Capacitance chart


	Size (Code)	CM316 (1206)
	Voltage (Vdc) citance (pF)	100
105	1000000	
106	2200000 4700000 10000000	D3 //

Two digits alphanumerics in capacitance chart denote dimensions and tan δ . Please refer to the above table for detail.

(Example) In case of "D3" for CM316;

L: 3.2 ± 0.20 mm W: 1.6 ± 0.20 mm T: 1.6 ± 0.20 mm Tan δ : 5.0% max.

Size	Size Code	Dir	Dimension (mm)								
Size	Code	L	W	Т							
316	D	3.2±0.20	1.6±0.20	1.6±0.20							
510	Е	3.2±0.30	1.6±0.30	1.6±0.30							



: Optional Spec.



Low Profile

CT Series

[RoHS Compliant Products]

■Features

This low profile series is ideal where height clearance is limited

■ Applications

Circuits requiring a compact, low-profile design, such as module and memory cards.

X5R Dielectric

Part Number List: P23

Capacitance chart

	Size Code)			CT105 (0603)			
<u> </u>	/oltage (Vdc) itance (pF)	6.3	6.3	16	16	25	50
104	100000	A8					
105	220000 470000 1000000	[D8]	[A8/B8]	A8		A3	
106	2200000 4700000 10000000		B8 }		E3		G3

: Optional Spec.

Two digits alphanumerics in capacitance chart denote dimensions and tan δ . Please refer to the below table for detail.

(Example) In case of "B8" for CT05;

L: 1.0±0.05mm $W: 0.5 \pm 0.05 mm$ T: 0.33mm max. Tan δ : 12.5% max.

Size	Size	Dimension (mm)						
Size	Code	L	W	Т				
03	Α	0.6±0.03	0.3±0.03	0.22 max.				
03	D	0.6±0.09	0.3±0.09	0.25 max.				
	Α	1.0±0.05	0.5±0.05	0.22 max.				
05	В	1.0±0.05	0.5±0.05	0.33 max.				
	Н	1.0±0.20	0.5 ± 0.20	0.33 max.				
105	Α	1.6±0.10	0.8±0.10	0.55 max.				
	Α	2.0±0.10	1.25±0.10	0.95 max.				
21	Е	2.0±0.15	1.25±0.15	0.95 max.				
	G	2.0±0.20	1.25±0.20	0.95 max.				

Tan δ Code	Tan δ
3	5.0%max.
8	12.5%max.
9	15.0%max.

High-Q

CU Series

[RoHS Compliant Products]

■Features

Ultra-miniature size (0.4x0.2mm) Low loss characteristics suitable for high frequency

Applications

RF power amplifier for mobiles such as impedance matching purpose.

Temperature Compensation Dielectric

Part Number List: P23

Capacitance chart

	ze Code)		CU02 (01005)		
	ance (pF)		16		
R20 R50	0.2 0.5				Г
1R0	1.0	ı			
1R5	1.5	ı			ĺ
	2.0	ī			Г
	3.0				
	4.0	Ц			L
	5.0	ı			
	6.0 7.0	ı		Α	
	8.0	Η	_		Н
	9.0	ı			ĺ
100	10				
120	12				
	15				ĺ
	18	4			⊢
	22				ட

· E12 Series

Please contact for capacitance value other than standard.

Alphabets in capacitance chart denote dimensions. Please refer to the below table for detail.

(Example)

In case of "A" for CU02; $L\,:0.4\!\pm\!0.02mm$

 $W: 0.2 \pm 0.02 mm$ T: $0.2 \pm 0.02 mm$

Size	Size Code	Dimension (mm)					
Size	Code	L	W	Т			
02	Α	0.4±0.02	0.2±0.02	0.2±0.02			



Au Termination AT Series

[RoHS Compliant Products]

■Features

Enables wire bonding, AuSn solder and conductive adhesive assembly by Au plated external termination electrodes.

■ Applications

- Optical communications
- Inside of IC packages

Part Number List: P24 X5R Dielectric

Capacitance chart

	AT02 (01005)		AT05 (0402)
Rated Voltage (Vdc) Capacitance (pF)	6.3	6.3	6.3
104 100000	A8 2		
220000			
470000		B8 2	1 8'64'3
105 1000000		C8 2	Willia
2200000		E8 2	

(Standard Capacitance Value)

Please contact for capacitance value other than standard.

: Optional Spec.

Two digits alphanumerics in capacitance chart denote dimensions and tan δ . Please refer to the below table for detail.

(Example)

In case of "B3" for AT03; L: 0.6±0.03mm W: 0.3±0.03mm $T: 0.3 \pm 0.03 mm$ Tan δ : 12.5% max.

Size	Size Code	Dimension (mm)					
Size	Code	L	W	Т			
02	Α	0.4±0.02	0.2±0.02	0.2±0.02			
	В	0.6±0.03	0.3±0.03	0.3±0.03			
03	С	0.6±0.05	0.3±0.05	0.3±0.05			
	Е	0.6±0.09	0.3±0.09	0.3±0.09			
05	С	1.0±0.05	0.5±0.05	0.5 ± 0.05			

Tan δ Code	Tan δ
7	10.0%max.
8	12.5%max.

Soft Termination ST Series

(RoHS Compliant Products)

Part Number List: P24

■Features

Realizes stress relief effect by soft termination which suppresses cracks in dielectrics.

Applications

 Electronic equipment for applications such as consumer and industrial uses.

X5R Dielectric

Capacitance chart

Size (EIA Code)	ST (02		ST05 (0402)		
Rated Voltage (Vdc) Capacitance (pF)	4	6.3	6.3	10	
105 1000000 2200000 4700000 106 10000000	[F8]	[C8]	[2 G8]] [3 J8]]	[D8]	

(Standard Capacitance Value)

Please contact for capacitance value other than standard.

: Optional Spec.

Two digits alphanumerics in capacitance chart denote dimensions and tan δ . Please refer to the below table for detail.

(Example)

In case of "D8" for ST05;


L: 1.0 ± 0.07mm W: 0.5 ± 0.07mm

 $T:0.5\pm0.07mm$ Tan δ : 12.5% max.

Size	Size	Dimension (mm)						
SIZE	Code	L	W	Т				
03	С	0.6±0.05	0.3±0.05	0.3±0.05				
03	F	0.6±0.10	0.3±0.10	0.3±0.10				
	D	1.0±0.07	0.5±0.07	0.5±0.07				
05	G	1.0±0.15	0.5 ± 0.15	0.5±0.15				
	J	1.0±0.20	0.5±0.20	0.5±0.20				

Tan δ Code	Tan δ
8	12.5%max.

■Structure






High Voltage CF Series

[RoHS Compliant Products]

■Features

Perform less than 1 fit failure ratio by high voltage durability and high reliability which has optimized internal electrode structure based on designing of safety.



· Mid-voltage range (Straight structure)

Secure break-down voltage margin with proper suitable dielectric thickness for each rated voltage.

· Mid-voltage range (Dual cascade structure)

Achieves high rated voltage by series connection of two capacitor units in one MLCC to divide applied voltage into two. Also, it has good protection against transient voltage.

· Mid-voltage range (Triple cascade structure)

Achieves high rated voltage by series connection of three capacitor units in one MLCC to divide applied voltage into three. Excellent safety against high voltage.

The multi cascade design prevents short circuit failure which results in excellent reliability

■ Applications

- Camera/ Strobe circuit, Surge killing, Trigger circui
- LCD back light inverter, Ballast capacitor
- ●Power circuit/ DC-DC converter, Snubber circuit

X7R Dielectric

Part Number List: P24-25

Capacitance chart

Capacitance (pr)	CF43 (1812))	CF42 (1808)		CF32 (1210)			CF316 (1206)		CF21 (0805)	Size IA Code)			
	000 2000	630 1000	250 630	000	2000	1000	1000	630	250	1000	630	250	250		
102 1000 B1 A1				A1	A1					В1					102
2200 4700 103 10000 D1 A1 B1 C1 A1 A1	A1					A1	A1			C1		Δ1		4700 10000	103
22000 47000 104 100000 220000	A1	A1 A1							В1		C1		ы	47000 100000	104

(Standard Capacitance Value)

• E3 Series

Please contact for capacitance value other than standard.

Two digits alphanumerics in capacitance chart denote dimensions and tan δ . Please refer to the below table for detail.

(Example)

In case of "B1" for CF21; L: 2.0 ± 0.1 mm W: 1.25 ± 0.1 mm T: 0.85 ± 0.1 mm Tan δ : 2.5% max.

Size	Size	Dii	Dimension (mm)					
Size	Code	L	W	Т				
	В	2.0±0.10	1.25±0.10	0.85±0.10				
21	С	2.0±0.10	1.25±0.10	1.05±0.10				
	D	2.0±0.10	1.25 ± 0.10	1.25±0.10				
	Α	3.2 ± 0.20	1.6±0.15	1.15±0.10				
316	В	3.2±0.20	1.6±0.15	1.25±0.10				
	С	3.2 ± 0.20	1.6±0.15	1.6±0.15				
32	А	3.2±0.30	2.5 ± 0.20	1.6±0.15				
32	В	3.2±0.30	2.5 ± 0.20	2.0 ± 0.20				
42	А	4.5 ± 0.20	2.0 ± 0.20	2.2 max.				
43	Α	4.5±0.30	3.2±0.20	2.5 max.				

anδ Code	Tan δ
1	2.5%max.



Three Terminal Capacitors KNH Series

[RoHS Compliant Products]

■Features

0402 Size. Rated current up to 2A MAX.

With unique circuit structure, this three terminal capacitor enables noise reduction in wide fequency range. With its high capacitance, it is possible to reduce the number of components being used.

Applications

- ●PCs, Laser Printers, Cellular Phone, Power/ Signal Lines for LCD Display, Office Equipments
- ●V Power Supply/ Signal Line, TV, VCR, etc.
- ●High Current Signal Lines

X5R Dielectric Part Number List: P25

Capacitance chart

	Size (EIA Code)							
	Voltage(Vdc) citance (pF)	4						
105	1000000							
435	4300000	[F]						
106	10000000	K 3						

· Storage condition Temperature: -10 to +45°C Humidity: 45 to 75%RH


Optional Spec.

Alphabets in capacitance chart denote dimensions. Please refer to the below table for detail.


In case of "K" for KNH05; L: 1.0±0.20mm $W: 0.5 \pm 0.20 mm$ $T: 0.5 \pm 0.20 mm$

Size	Dimension (mm)							
Code	L W T G P F							
F	1.0±0.10	0.5±0.20	0.50 max.	0.3±0.10	0.15±0.10	≥0.05		
K	1.0±0.20	0.5±0.20	0.5±0.20	0.3±0.10	0.15±0.10	≥0.05		

Dimension



■ Recommended Land Pattern (Unit: mm)





Test Conditions and Standards

Test Conditions and Specifications for Temperature Compensation Type (C Δ Characteristics) CM / CU Series

Test Items		Test Conditi	ons	Specifications		
Capacitance V	alue (C)	Capacitance Frequency	Volt	Within tolerance		
Q		C≤1000pF 1MHz ± 10% C>1000pF 1kHz ± 10% 0.5 to 5Vrms		C≥30pF: Q≥1000 C<30pF: Q≥400+20C		
Insulation Resistance (IR)		Measured after the rated volt minute at room ambient. The charge and discharge cur tor must not exceed 50mA.		Over $10000M\Omega$ or $500M\Omega$ • μF , whichever is less		
Dielectric Resis	tance	Apply 3 times of the rated voltage. The charge and discharge curtor must not exceed 50mA.		No problem observed		
Appearance		Microscope		No problem observed		
Termination St	rength	Apply a sideward force of 500 mounted sample. Apply 2N for 01005 size.		No problem observed		
Bending Streng	gth	Glass epoxy PCB: Fulcrum spac time 10 seconds.	ng: 90mm, duration	No significant damage at 1mm bent		
Vibration	Appearance	Vibration frequency: 10 to 55	(Hz)	No problem observed		
Test	ΔC	Amplitude: 1.5mm Sweeping condition: 10 → 55 -	→ 10Hz/ 1 minute	Within Tolerance		
	Sweeping condition: $10 \rightarrow 55 \rightarrow 10$ Hz/ 1 minute in X, Y and Z Directions: 2 hours each, 6 hours total.		C≥30pF: Q≥1000 C<30pF: Q≥400+20C			
Soldering	Appearance	Soak the sample in 260°C \pm 5 \pm 0.5 seconds and place in re		No problem observed		
Heat Resistance	ΔC	measure after 24 \pm 2 hours.	om ambient, and	Within \pm 2.5% or \pm 0.25pF, whichever is larger		
_	Q	(Pre-heating conditions) Order Temperature	Time	C≥30pF: Q≥1000 C<30pF: Q≥400+20C		
	IR	1 80 to 100°C	2 minutes	Over $10000M\Omega$ or $500M\Omega \cdot \mu F$ whichever is less		
	Withstanding Voltage	2 150 to 200°C 2 minutes The charge and discharge current of the capacitor must not exceed 50mA for IR and withstanding voltage measurement.		Resist without problem		
Solderablity		Soaking condition Sn-3Ag-0.5Cu 245 ± 5 Sn63 Solder 235 ± 5	°C 3 ± 0.5 sec. °C 2 ± 0.5 sec.	Solder coverage : 90% min.		
Temperature	Appearance	(Cycle)		No problem observed		
Cycle	ΔC	Room temperature (3min.) →		Within \pm 2.5% or \pm 0.25pF, whichever is larger		
	Q	Lowest operation temperature Room temperature (3min.) →		C≥30pF : Q≥1000 C<30pF : Q≥400+20C		
	IR	Highest operation temperature	e(30min.)	Over $10000M\Omega$ or $500M\Omega$ · μF , whichever is less		
	Withstanding Voltage	After 5 cycles, measure after The charge and discharge cur tor must not exceed 50mA foing voltage measurement.	rent of the capaci-	Resist without problem		
Load	Appearance	After applying rated voltage		No problem observed		
Humidity Test	ΔC	hours in pre-condition at 40°C 90 to 95%RH, allow parts to s		Within \pm 7.5% or \pm 0.75pF, whichever is larger		
	Q	2 hours, at room temperature ment.	before measure-	C≥30pF: Q≥200 C<30pF: Q≥100+10C/3		
	IR	The charge and discharge cur tor must not exceed 50mA for		Over $500M\Omega$ or $25M\Omega \cdot \mu F$, whichever is less		
High-	Appearance	After applying twice the rate	d voltage at the	No problem observed.		
Temperature with Loading	ΔC	temperature of 125 \pm 3°C fo	r 1000+12/ - 0	Within \pm 3% or \pm 0.3pF, whichever is larger		
3	Q	hours, measure the sample aff The charge and discharge cur capacitor must not exceed 50	rent of the	C≥30pF: Q≥350 10pF <c<30pf: 2<br="" q≥275+5c="">C<10pF: Q≥200+10C</c<30pf:>		
		measurement.				

Please ask for individual specification for the hatched range in previous chart.



Test Conditions and Standards

Test Conditions and Specifications for High Dielectric Type (X5R, X7R) CM / CT Series

Test Items		Test Conditions	Specifications		
Capacitance Value (C)		Measure after heat treatment	Within tolerance		
Ταηδ		Capacitance Frequency Volt C≤10µF 1kHz ± 10% 1.0 ± 0.2Vrms C>10µF 120Hz ± 10% 0.5 ± 0.2Vrms	Refer to capacitance chart		
Insulation Resistance (IR)		Measured after the rated voltage is applied for 1 minute at room ambient. The charge and discharge current of the capacitor must not exceed 50mA.	Over $10000M\Omega$ or $500M\Omega$ · μF , whichever is less		
Dielectric Resis	tance	Apply 2.5 times of the rated voltage for 1 to 5 seconds. The charge and discharge current of the capacitor must not exceed 50mA.	No problem observed		
Appearance		Microscope	No problem observed		
Termination St	rength	Apply a sideward force of 500g (5N) to a PCB-mounted sample. note: 2N for 0201 size, and 1N for 01005 size. Exclude CT series with thickness of less than 0.66mm.	No problem observed		
Bending Streng	th	Glass epoxy PCB: Fulcrum spacing: 90mm, duration time 10 seconds. Exclude CT series with thickness of less than 0.66mm.	No significant damage at 1mm bent		
Vibration Appearance		Take the initial value after heat treatment. Vibration frequency: 10 to 55 (Hz)	No problem observed		
	ΔC	Amplitude: 1.5mm Sweeping condition: 10→55→10Hz/ 1 minute in X, Y and Z	Within tolerance		
	Ταηδ	Directions: 2 hours each, 6 hours total, and place in room ambient, and measure the sample after heat treatment.	Within tolerance		
Soldering Heat	Appearance	Take the initial value after heat treatment. Soak the sample in $260^{\circ}C \pm 5^{\circ}C$ solder for 10	No problem observed		
Resistance	ΔC	± 0.5 seconds and place in room ambient, and measure after heat treatment.	Within ± 7.5%		
	Ταηδ	(Pre-heating conditions)	Within tolerance		
	IR	Order Temperature Time 1 80 to 100°C 2 minutes	Over $10000M\Omega$ or $500M\Omega$ · μF , whichever is less		
	Withstanding Voltage	2 150 to 200°C 2 minutes The charge and discharge current of the capacitor must not exceed 50mA for IR and withstanding voltage measurement.	Resist without problem		
Solderablity		Soaking condition Sn-3Ag-0.5Cu	Solder coverage : 90% min.		
Temperature	Appearance	Take the initial value after heat treatment.	No problem observed		
Cycle	ΔC	(Cycle) Room temperature (3min.)→	Within ± 7.5%		
	Tanδ	Lowest operation temperature (30min.)→	Within tolerance		
	Withstanding Voltage	Room temperature (3min.)— Highest operation temperature(30min.) After 5 cycles, measure after heat treatment. The charge and discharge current of the capacitor must not exceed 50mA for IR and withstanding voltage measurement.	Over $10000M\Omega$ or $500M\Omega$ • μF , whichever is less Resist without problem		
Load Humidity	Appearance	Take the initial value after heat treatment. After applying rated voltage for 500+12/-0	No problem observed		
Test	ΔC	hours in pre-condition at 40° C \pm 2° C, humidity	Within ± 12.5%		
	Tanδ	90 to 95%RH, and place in room ambient, and measure the sample after heat treatment.	200% max. of initial value		
	IR	The charge and discharge current of the capacitor must not exceed 50mA for IR measurement.	Over $500 \text{M}\Omega$ or $25 \text{M}\Omega$ · μF , whichever is less		
High- Temperature	Appearance	Take the initial value after heat treatment. After applying twice the rated voltage at the	No problem observed		
with Loading	ΔC	highest operation temperature for $1000+12/-0$ hours, measure the sample after heat treatment.	Within ± 12.5%		
	Ταηδ	The charge and discharge current of the capacitor must not exceed 50mA for IR measurement.	200% max. of initial value		
	IR	Apply 1.5 times when the rated voltage is 10V or less. Applied voltages for respective products are indicated in the below chart.	Over $1000M\Omega$ or $50M\Omega$ · μF , whichever is less		

Heat treatment Keep specimen at $150+0/-10^{\circ}$ C for 1 hour, leave specimen at room ambient for 24 ± 2 hours.

High-temperature with Loading Applied Voltage (Rated Voltage $\overline{\times \square}$)

	, p 0 : 0 : 1 : 1	With Educing Applied Voltage (Nated Voltage X 🗆)
Applied Voltage	Rated Voltage	Products Products
×1.3	×1.3 6.3V	CM105X5R475, CM02X5R153-104
× 1.5	0.5 V	CT03X5R104
	16\/	CM02X7R101-222, CM105X7R105, CM21X7R475, CM316X7R106, CM32X7R226, CM05X5R224, CM105X5R225, CM21X5R475-106, CM316X5R226
	16V	CT105X5R105, CT21X5R225-475, CM02X5R101-103
		CM21X7R105-225, CM316X7R475, CM32X7R106, CM105X5R105, CM21X5R225-475, CM316X5R106,
×1.5	25V	CM32X5R106-226
		CM03X5R152-103, CM05X7R104
	50\/	CM21X5R105, CM32X5R106, CM32X7R106
	50V	CT21X5R225

Please ask for individual specification for the hatched range in previous chart.



Test Conditions and Standards

Test Conditions and Specifications for High Dielectric Type (X7R) CF Series

Test Items		Test Conditions	Specifications	
Capacitance Value (C)		Measure after heat treatment	Within tolerance	
Capacitance Value (C) Tanδ		CapacitanceFrequencyVoltC≤10µF1kHz ± 10%1.0 ± 0.2Vrms	Within 2.5%	
Insulation Resistance (IR)		Measured after the rated voltage is applied for 1 minute at room ambient. Measured after the 500V is applied for 1 minute at room ambient for the rated voltage over 630V. The charge and discharge current of the capacitor must not exceed 50mA.	Over $10000M\Omega$ or $500M\Omega$ · μF , whichever is less Over $100M\Omega$ · μF for CF316X7R104/ 250V	
Dielectric Resis	tance	Apply 1.5 times when the rated voltage is 250V or over, apply 1.2 times when the rated voltage is 630V or over for 1 to 5 seconds. The charge and discharge current of the capacitor must not exceed 50mA.	No problem observed	
Appearance		Microscope	No problem observed	
Termination St	rength	Apply a sideward force of 500g (5N) to a PCB-mounted sample.	No problem observed	
Bending Streng	gth	Glass epoxy PCB: Fulcrum spacing: 90mm, duration time 10 seconds.	No significant damage at 1mm bent	
Vibration Appearance		Take the initial value after heat treatment.	No problem observed	
Test	ΔC	Vibration frequency: 10 to 55 (Hz) Amplitude: 1.5mm	Within tolerance	
Tanδ		Sweeping condition: $10\rightarrow55\rightarrow10$ Hz/ 1 minute in X, Y and Z Directions: 2 hours each, 6 hours total.	Within tolerance	
Soldering	Appearance	Take the initial value after heat treatment.	No problem observed	
Heat Resistance	ΔC	Soak the sample in 260°C \pm 5°C solder for 10 \pm 0.5 seconds and place in room	Within ± 7.5%	
	Tanδ(%)	ambient, and measure after heat treatment. (Pre-heating conditions)	Within tolerance	
	IR	Order Temperature Time 1 80 to 100°C 2 minutes	Over $10000M\Omega$ or $500M\Omega$ · μ F, whichever is less Over $100M\Omega$ · μ F for CF316X7R104/ 250V and CF55X7R224/ 630V	
	Withstanding Voltage	2 150 to 200°C 2 minutes The charge and discharge current of the capacitor must not exceed 50mA for IR and withstanding voltage measurement.	Resist without problem	
Solderablity		Soaking condition Sn-3Ag-0.5Cu $245 \pm 5^{\circ}$ C 3 ± 0.5 sec. Sn63 Solder $235 \pm 5^{\circ}$ C 2 ± 0.5 sec.	Solder coverage : 90% min.	
Temperature	Appearance	Take the initial value after heat treatment.	No problem observed	
Cycle	ΔC	(Cycle) Room temperature (3min.)→	Within ± 7.5%	
	Tanδ	Lowest operation temperature (30min.)→ Room temperature (3min.)→	Within tolerance	
	IR	Highest operation temperature(30min.) After 5 cycles, measure after heat	Over $10000M\Omega$ or $500M\Omega \cdot \mu F$, whichever is less Over $100M\Omega \cdot \mu F$ for CF316X7R104/ 250V	
	Withstanding Voltage	treatment. The charge and discharge current of the capacitor must not exceed 50mA for IR and withstanding voltage measurement.	Resist without problem	
High- Temperature	Appearance	Take the initial value after heat treatment. After applying specified voltage at the highest	No problem observed	
with Loading	ΔC	operation temperature for 1000+12/ - 0 hours, then measure the sample after heat treatment. The applied voltage shall be;	Within ± 12.5%	
	Tanδ	1.5 times the rated voltage when the rated voltage is 250V.1.2 times when the rated voltage is 630V or over.	200% max. of initial value	
	IR	The charge and discharge current of the capacitor must not exceed 50mA for IR measurement.	Over $1000M\Omega$ or $50M\Omega$ · μF , whichever is less	
Heat treatme	nt	Keep specimen at 150+0/-10°C for 1 hour	r, leave specimen at room ambient for 24 ± 2 hours.	




(Unit: mm)

3.7

Test Conditions and Standards

Substrate for Adhesion Strength Test, Vibration Test, Soldering Heat Resistance Test, Temperature Cycle Test, Load Humidity Test, High-Temperature with Loading Test.



Size (EIA Code)	a	b	С
02 (01005)	0.15	0.50	0.20
03 (0201)	0.26	0.92	0.32
05 (0402)	0.4	1.4	0.5
105 (0603)	1.0	3.0	1.2
21 (0805)	1.2	4.0	1.65
316 (1206)	2.2	5.0	2.0
32 (1210)	2.2	5.0	2.9
42 (1808)	3.5	7.0	3.7


7.0

Substrate for Bending Test

(Unit: mm)

43 (1812)

3.5




 $^{^*}$ 02, 03, 05 size 0.8 \pm 0.1mm



Packaging Options

Tape and Reel

· Reel



Reel

(Unit: mm)


Code Reel	АВ		С	D
7-inch Reel (CODE: T, H, Q)	180 +0			
7-inch Reel (CODE: P)	178 ± 2.0	φ 60 min.	13±0.5	21±0.8
13-inch Reel (CODE: L, N, W)	330 ± 2.0			
Code	Е	W ₁	W ₂	D
Reel	_	VV 1	VV2	R
7-inch Reel (CODE: T, H, Q)		10.5 ± 1.5	16.5 max.	К
7-inch Reel	2.0±0.5			1.0

^{*} Carrier tape width 8mm.

For size 42 (1808) or over, Tape width 12mm and W1: 14 \pm 1.5, W2: 20.5mm max.


Carrier Tape


F=1mm (02 Type)







F=4mm (105, 21, 316, 32, 42 Type)







F=1mm (02, 03, 05 Type)






F=8mm (43 Type)





F=2mm (02, 03, 05 Type)





Carrier Tape (Unit: mm)


Size	А	В	С	D	Е	F	G	Н	1	Carrie	r Tape
(EIA Code)	A	Ь	C	D			G		J	Width	Material
02 (01005)*	0.23 ± 0.02	0.43 ± 0.02	4.0±0.08	1.8 ± 0.02	0.9 ± 0.05	1.0 ± 0.02		2.0±0.04	0.8 ± 0.04	4mm	Plastic
02 (01003)	0.25 ± 0.03	0.45 ± 0.03	8.0±0.3	3.5 ± 0.05	1.75±0.1	2.0 ± 0.05	_	4.0 ± 0.1	1.5+0.1/-0	8mm	Paper
03 (0201)*	0.37±0.03	0.67±0.03	8.0+0.3/-0.1	3.5±0.05	1.75±0.1	1.0 ± 0.05	_	4.0±0.05	1.5+0.1/-0	8mm	Paper
03 (0201)	0.57 ± 0.05	0.67 ± 0.03	8.0 ± 0.3	3.5 ± 0.05	1.75 ± 0.1	2.0±0.05	_	4.0 ± 0.1	1.5 (0.1/ 0	OTTITI	Гарег
	0.65±0.1		8.0+0.3/-0.1			1.0 ± 0.05	_	4.0 ± 0.05			
05 (0402)*	0.05 ± 0.1	1.15±0.1	8.0±0.3	3.5 ± 0.05	1.75 ± 0.1	2.0±0.05		4.0±0.1	1.5+0.1/-0	8mm	Paper
	0.75 ± 0.1		0.0 ± 0.3			2.0 ± 0.05	_	4.0 ± 0.1			
105 (0603)	1.0 ± 0.2	1.8±0.2	8.0 ± 0.3	3.5 ± 0.05	1.75±0.1	4.0 ± 0.1	2.0 ± 0.05	4.0 ± 0.1	1.5+0.1/-0	8mm	Paper
21 (0805)	1.5 ± 0.2	2.3±0.2	8.0±0.3	3.5±0.05	1.75±0.1	4.0±0.1	2.0±0.05	4.0±0.1	1.5+0.1/-0	8mm	Paper
21 (0803)	1.5 ± 0.2	2.3 ± 0.2	6.0 ± 0.3	3.5 ± 0.05	1.75 ± 0.1	4.0 ± 0.1	2.0 ± 0.05	4.0 ± 0.1	1.5 0.1/ 0	8mm	Plastic
316 (1206)	2.0±0.2	3.6±0.2	8.0±0.3	3.5±0.05	1.75±0.1	4.0±0.1	2.0±0.05	4.0±0.1	1.5+0.1/-0	8mm	Paper
310 (1200)	2.0 ± 0.2	3.0 ± 0.2	0.0 ± 0.3	3.5 ± 0.05	1.75 ± 0.1	4.0 ± 0.1	2.0 ± 0.05	4.0 ± 0.1	1.5 + 0.1/ 0	8mm	Plastic
32 (1210)	2.9 ± 0.2	3.6±0.2	8.0±0.3	3.5 ± 0.05	1.75±0.1	4.0 ± 0.1	2.0±0.05	4.0 ± 0.1	1.5+0.1/-0	8mm	Plastic
42 (1808)	2.4 ± 0.2	4.9 ± 0.2	12.0±0.3	5.5 ± 0.05	1.75±0.1	4.0 ± 0.1	2.0±0.05	4.0 ± 0.1	1.5+0.1/-0	12mm	Plastic
43 (1812)	3.6 ± 0.2	4.9 ± 0.2	12.0±0.3	5.5 ± 0.05	1.75±0.1	8.0±0.1	2.0±0.05	4.0 ± 0.1	1.5+0.1/-0	12mm	Plastic

^{*} Option




Packaging Options

Detail of leader and trailer



Adhesive tape

- 1) The exfoliative strength when peeling off the top tape from the carrier tape by the method of the following figure shall be *0.1 to 0.7N. *02 Size: 0.1 to 0.5N
- 2) When the top tape is peeled off, the adhesive stays on the top tape.
- 3) Chip capacitors will be in a state free without being stuck on the thermal adhesive tape.



Exfoliating angle: 165 to 180 degrees to the carrier tape. Exfoliating speed: 300 mm/min.

Carrier tape

- 1) Chip will not fall off from carrier tape or carrier tape will not be damaged by bending than within a radius of 25mm.
- 2) The chip are inserted continuously without any empty pocket.
- 3) Chip will not be mis-mounted because of too big clearance between components and cavity. Also the waste of carrier tape will not fill a nozzle hole of mounting machine.

Packaging quantity

Please refer to Page 2.




Surface Mounting Information

Dimensions for recommended typical land

Since the amount of solder (size of fillet) to be used has direct influence on the capacitor after mounting, the sufficient consideration is necessary.

When the amounts of solder is too much, the stress that a capacitor receives becomes larger. It may become the cause of a crack in the capacitor. When the land design of printed wiring board is considered, it is necessary to set up the form and size of land pattern so that the amount of solder is suitable.



General, High-Voltage

(Unit: mm)


Size (EIA Code)	L×W	a	b	С
02 (01005)	0.4×0.2	0.13 to 0.20	0.12 to 0.18	0.20 to 0.23
03 (0201)	0.6×0.3	0.20 to 0.30	0.25 to 0.35	0.30 to 0.40
05 (0402)	1.0×0.5	0.30 to 0.50	0.35 to 0.45	0.40 to 0.60
105 (0603)	1.6×0.8	0.70 to 1.00	0.80 to 1.00	0.60 to 0.80
21 (0805)	2.0×1.25	1.00 to 1.30	1.00 to 1.20	0.80 to 1.10
316 (1206)	3.2×1.6	2.10 to 2.50	1.10 to 1.30	1.00 to 1.90
32 (1210)	3.2×2.5	2.10 to 2.50	1.10 to 1.30	1.90 to 2.30
42 (1808)	4.5×2.0	3.00 to 3.50	1.80 to 2.30	1.50 to 1.80
43 (1812)	4.5×3.2	3.00 to 3.50	1.80 to 2.30	2.60 to 3.00

^{*} Recommended land dimensions may differ depending on dimensional tolerance.

Design of printed circuit and Soldering

The recommended fillet height shall be 1/2 of the thickness of capacitors or 0.5mm. When mounting two or more capacitors in the common land, it is necessary to separate the land with the solder resist strike so that it may become the exclusive land of each capacitor.

Ideal Solder Height



Item	Not recommended example	Recommended example/ Separated by solder
Multiple parts mount		Solder resist
Mount with leaded parts	Leaded parts	Solder resist Leaded parts
Wire soldering after mounting	Soldering iron Wire	Solder resist
Overview	Solder resist	Solder resist





Surface Mounting Information

Mounting Design

The chip could crack if the PCB warps during processing after the chip has been soldered.


Recommended chip position on PCB to minimize stress from PCB warpage






Actual Mounting

- 1) If the position of the vacuum nozzle is too low, a large force may be applied to the chip capacitor during mounting, resulting in cracking.
- 2) During mounting, set the nozzle pressure to a static load of 1 to 3 N.
- 3) To minimize the shock of the vaccum nozzle, provide a support pin on the back of the PCB to minimize PCB flexture.





4) Bottom position of pick up nozzle should be adjusted to the top surface of a substrate which camber is corrected.

Resin Mold

- 1) If a large amount of resin is used for molding the chip, cracks may occur due to contraction stress during curing. To avoid such cracks, use a low shrinkage resin.
- 2) The insulation resistance of the chip will degrade due to moisture absorption. Use a low moisture absorption resin.
- 3) Check carefully that the resin does not generate a decomposition gas or reaction gas during the curing process or during normal storage. Such gases may crack the chip capacitor or damage the device itself.




Surface Mounting Information

Soldering Method


- 1) Ceramic is easily damaged by rapid heating or cooling. If some heat shock is unavoidable, preheat enough to limit the temperature difference (Delta T) to within 150 degree Celsius.
- 2) The product size 1.6×0.8mm to 3.2×1.6mm can be used in reflow and wave soldering, and the product size of bigger than 3.2×1.6mm, or smaller than 1.6×0.8mm can be used in reflow.
 - Circuit shortage and smoking can be created by using capacitors which are used neglecting the above caution.
- 3) Please see our recommended soldering conditions.
- 4) In case of using Sn-Zn Solder, please contact us in advance.
- 5) The following condition is recommended for spot heater application.

· Recommended spot heater condition

Item	Condition
Distance	5mm min.
Angle	45°
Projection Temp.	400°C max.
Flow rate	Set at the minimum
Nozzle diameter	2Φ to 4Φ (Single hole type)
Application time	10 sec. max. (1206 and smaller) 30 sec.max. (1210 and larger)



Recommended Temperature Profile (Sn-3Ag-0.5Cu) Reflow 250°C±5°C 300 Preheat 250 Cool at normal 00 200 170 to 180°C 150 100 50 90±30 sec. ① Minimize soldering time. ② Ensure that allowable temperature difference does not exceed 150°C. ③ Ensure that allowable temperature difference does not exceed 130°C for 3.2×2.5mm size or larger. Wave Peak Temperatur 245°C to 260°C 250 ွ 200 100 0 5 sec. max 60 to 120 sec.



Soldering iron

1) Temperature of iron chip

① Ensure that the chip capacitor is preheated adequately. ② Ensure that the temperature difference (ΔT) does not exceed 150°C.

1206 and smaller 350°C max. 5) Cautions

1210 and larger 280°C max.

2) Wattage

3) Tip shape of soldering iron

4) Soldering Time

80W max.

3 sec. max.

Cool naturally after soldering.
 Wave soldering is not applicable for chips with size of 3.2×2.5mm or larger of 1.0×0.5mm or smaller and capacitor arrays

 ϕ 3.0mm max.

a) Pre-heating is necessary rapid heating must be avoided. Delta T≤150°C (product size of bigger than 3.2×1.6mm. Delta T≤130°C)

- b) Avoid direct touching to capacitors.
- c) Avoid rapid cooling after soldering. Natural cooling is recommended.

 * Consult as if it is difficult to keep the temperature 280°C max. for 1210 and larger MLCC'S.



Precautions

Circuit Design

- 1. Once application and assembly environments have been checked, the capacitor may be used in conformance with the rating and performance which are provided in both the catalog and the specifications. Use exceeding that which is specified may result in inferior performance or cause a short, open, smoking, or flaming to occur, etc.
- 2. Please consult the manufacturer in advance when the capacitor is used in devices such as: devices which deal with human life, i.e. medical devices; devices which are highly public orientated; and devices which demand a high standard of liability.
 Accident or malfunction of devices such as medical devices, space equipment and devices having to do with atomic power could generate grave consequence with respect to human lives or, possibly, a portion of the public. Capacitors used in these devices may require high reliability design different from that of general purpose capacitors.
- 3. Please use the capacitors in conformance with the operating temperature provided in both the catalog and the specifications.

 Be especially cautious not to exceed the maximum temperature. In the situation the maximum temperature set forth in both the catalog and specifications is exceeded, the capacitor's insulation resistance may deteriorate, power may suddenly surge and short-circuit may occur. The capacitor has a loss, and may self-heat due to equivalent series resistance when alternating electric current is passed therethrough. As this effect becomes especially pronounced in high frequency circuits, please exercise caution.

 When using the capacitor in a (self-heating) circuit, please make sure the surface of the capacitor remains under the maximum temperature for usage. Also, please make certain temperature rises remain below 20°C.
- 4. Please keep voltage under the rated voltage which is applied to the capacitor. Also, please make certain the peak voltage remains below the rated voltage when AC voltage is super-imposed to the DC voltage.
 In the situation where AC or pulse voltage is employed, ensure average peak voltage does not exceed the rated voltage.
 Exceeding the rated voltage provided in both catalog and specifications may lead to defective withstanding voltage or, in worst case situations, may cause the capacitor to smoke or flame.
- 5. When the capacitor is to be employed in a circuit in which there is continuous application of a high frequency voltage or a steep pulse voltage, even though it is within the rated voltage, please inquire to the manufacturer.
 In the situation the capacitor is to be employed using a high frequency AC voltage or a extremely fast rising pulse voltage, even though it is within the rated voltage, it is possible capacitor reliability will deteriorate.
- 6. It is a common phenomenon of high-dielectric products to have a deteriorated amount of static electricity due to the application of DC voltage. Due caution is necessary as the degree of deterioration varies depending on the quality of capacitor materials, capacity, as well as the load voltage at the time of operation.
- 7. Do not use the capacitor in an environment where it might easily exceed the respective provisions concerning shock and vibration specified in the catalog and specifications.
 In addition, it is a common piezo phenomenon of high dielectric products to have some voltage due to vibration or to have noise due to voltage change. Please contact sales in such case.
- 8. If the electrostatic capacity value of the delivered capacitor is within the specified tolerance, please consider this when designing the respective product in order that the assembled product function appropriately.
- 9. Please contact us upon using conductive adhesives.

Storage

- 1. If the component is stored in minimal packaging (a heat-sealed or zippered plastic bag), the bag should be kept closed. Once the bag has been opened, reseal it or store it in a desiccator.
- 2. Keep storage place temperature + 5 to + 40 degree C, humidity 20 to 70% RH. See JIS C 60721-3-1, class 1K2 for other climatic conditions.
- 3. The storage atmosphere must be free of corrosive gas such as sulfur dioxide and chlorine. Also, avoid exposing the product to saline moisture. If the product is exposed to such atmospheres, the terminals will oxidize and solderability will be effected.
- 4. Precautions 1) to 3) apply to chip capacitors packaged in carrier tapes.
- 5. The solderability is assured for 6 months from our shipping date if the above storage precautions are followed.

Safety application guideline and detailed information of electrical properties are also provided in Kyocera web site; URL: https://global.kyocera.com/prdct/electro/





General CM02 Series Size (JIS Code): 01005(0402) # Packaging Code (Packaging quantity): H(20,000pcs.) / N(80,000pcs.) / P(40,000pcs.)

Dielectric code	David Niverda av	C:	D.T.J	Voltage		Dimension		0
СФ	Part Number	Capacitance	□:Tolerance	[V]	L[mm]	W[mm]	T[mm]	Q
	CM02C △ 1R0 □ 25A#	1pF	B:±0.1pF / C:±0.25pF					420
	CM02C △ 1R5 □ 25A#	1.5pF	B:±0.1pF / C:±0.25pF					430
	CM02C ∆ 2R0 □ 25A#	2pF	B:±0.1pF / C:±0.25pF					440
	CM02C ∆ 3R0 □ 25A#	3pF	$B:\pm 0.1pF / C:\pm 0.25pF$					460
	CM02C △ 4R0 □ 25A#	4pF	$B:\pm 0.1pF / C:\pm 0.25pF$					480
	CM02C ∆ 5R0 □ 25A#	5pF	$B:\pm 0.1pF / C:\pm 0.25pF$					500
	CM02C △ 6R0 □ 25A#	6pF	$C:\pm 0.25pF / D:\pm 0.5pF$					520
	CM02C △ 7R0 □ 25A#	7pF	$C:\pm 0.25pF / D:\pm 0.5pF$	25	0.4 ± 0.02	0.2 ± 0.02	0.2 ± 0.02	540
	CM02C △ 8R0 □ 25A#	8pF	$C:\pm 0.25pF / D:\pm 0.5pF$					560
	CM02C △ 9R0 □ 25A#	9pF	$C:\pm 0.25pF / D:\pm 0.5pF$					580
	CM02C ∆ 100 □ 25A#	10pF	J:±5% / K:±10%					600
	CM02C ∆ 120 □ 25A#	12pF	J:±5% / K:±10%					640
	CM02C ∆ 150 □ 25A#	15pF	J:±5% / K:±10%					700
CG/CH	CM02C ∆ 180 □ 25A#	18pF	J:±5% / K:±10%					760
	CM02C ∆ 220 □ 25A#	22pF	J:±5% / K:±10%					840
	CM02C △ 270 □ 16A#	27pF	J:±5% / K:±10%					940
	CM02C △ 330 □ 16A#	33pF	J: ± 5% / K: ± 10%					
	CM02C △ 390 □ 16A#	39pF	J: ± 5% / K: ± 10%					
	CM02C △ 470 □ 16A#	47pF	J: ± 5% / K: ± 10%					
	CM02C △ 560 □ 16A#	56pF	J: ± 5% / K: ± 10%					
	CM02C △ 680 🗆 16A#	68pF	J: ± 5% / K: ± 10%	16	0.4±0.02	0.2 ± 0.02	0.2±0.02	
	CM02C △ 820 □ 16A#	82pF	J:±5% / K:±10%] '0	0.4 = 0.02	0.2 = 0.02	0.2 = 0.02	1000
(CM02C △ 101 ☐ 16A#	100pF	J:±5% / K:±10%					
	CM02C △ 121 ☐ 16A#	120pF	J:±5% / K:±10%]				
	CM02C △ 151 ☐ 16A#	150pF	J:±5% / K:±10%]				
	CM02C △ 181 ☐ 16A#	180pF	J:±5% / K:±10%]				
	CM02C △ 221 ☐ 16A#	220pF	J:±5% / K:±10%					

General CM03 Series Size (JIS Code): 0201(0603) # Packaging Code (Packaging quantity): H(15,000pcs.) / N(50,000pcs.) / Q(30,000pcs.) / W(150,000pcs.)


Dielectric code	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Q
CΔ	Fart Number	Capacitarice	□.1 oler arice	[V]	L[mm]	W[mm]	T[mm]	w w
	CM03C △ 1R0 □ 50A#	1pF	$B:\pm 0.1pF / C:\pm 0.25pF$					420
[CM03C ∆ 1R5 □ 50A#	1.5pF	B: $\pm 0.1pF / C: \pm 0.25pF$					430
	CM03C ∆ 2R0 □ 50A#	2pF	B: $\pm 0.1 pF / C$: $\pm 0.25 pF$					440
	CM03C △ 3R0 □ 50A#	3pF	B: ± 0.1pF / C: ± 0.25pF					460
	CM03C △ 4R0 □ 50A#	4pF	B: $\pm 0.1 pF / C$: $\pm 0.25 pF$					480
	CM03C △ 5R0 □ 50A#	5pF	B: $\pm 0.1 pF / C$: $\pm 0.25 pF$					500
	CM03C △ 6R0 □ 50A#	6pF	$C:\pm 0.25pF / D:\pm 0.5pF$					520
	CM03C △ 7R0 □ 50A#	7pF	$C:\pm 0.25pF / D:\pm 0.5pF$					540
	CM03C △ 8R0 □ 50A#	8pF	$C:\pm 0.25pF / D:\pm 0.5pF$					560
[CM03C △ 9R0 □ 50A#	9pF	$C:\pm 0.25pF / D:\pm 0.5pF$					580
	CM03C △ 100 □ 50A#	10pF	J:±5% / K:±10%					600
CG/CH	CM03C △ 120 □ 50A#		0.3 ± 0.03	640				
		15pF	J:±5% / K:±10%					700
	CM03C △ 180 □ 50A#	18pF	J:±5% / K:±10%					760
	CM03C △ 220 □ 50A#	22pF	J:±5% / K:±10%					840
	CM03C △ 270 □ 50A#	27pF	J: ± 5% / K: ± 10%					940
	CM03C △ 330 □ 50A#	33pF	J: ± 5% / K: ± 10%					
	CM03C △ 390 □ 50A#	39pF	J: ± 5% / K: ± 10%					
	CM03C △ 470 □ 50A#	47pF	J: ± 5% / K: ± 10%					
	CM03C △ 560 □ 50A#	56pF	J:±5% / K:±10%					1000
	CM03C △ 680 □ 50A#	68pF	J:±5% / K:±10%					
	CM03C △ 820 □ 50A#	82pF	J:±5% / K:±10%	1				
	CM03C △ 101 □ 50A#	100pF	J:±5% / K:±10%					

General CM05 Series Size (JIS Code): 0402(1005) # Packaging Code (Packaging quantity): H(10,000pcs.) / N(50,000pcs.) / Q(20,000pcs.) / W(100,000pcs.)

Dielectric code	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Q
CΔ	Fart Number	Capacitance	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	٧
	CM05C △ 121 □ 50A#	120pF	J:±5% / K:±10%					
	CM05C △ 151 □ 50A#	150pF	J:±5% / K:±10%					
	CM05C △ 181 □ 50A#	180pF	J:±5% / K:±10%	50	1.0±0.05	0.5±0.05	0.5±0.05	
CG/CH	CM05C △ 221 □ 50A#	220pF	J:±5% / K:±10%					1000
CG/CH	CM05C △ 271 □ 50A#	270pF	J:±5% / K:±10%	30	1.0 ± 0.05	0.5 ± 0.05	0.5 ± 0.05	1000
	CM05C △ 331 □ 50A#	330pF	J:±5% / K:±10%					
	CM05C △ 391 □ 50A#	390pF	J:±5% / K:±10%					
	CM05C △ 471 □ 50A#	470pF	J:±5% / K:±10%					

General CM105 Series Size (JIS Code): 0603(1608) # Packaging Code (Packaging quantity): T(4,000pcs.) / L(10,000pcs.)

Dielectric code	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		0
CΔ	Fart Number	Capacitarice	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	ا
	CM105C △ 561 □ 50A#	560pF	J:±5% / K:±10%					
CG/CH	CM105C △ 681 □ 50A#	680pF	J:±5% / K:±10%	50	1.6±0.10	0.8±0.10	0.8±0.10	1000
CG/CH	CM105C △ 821 □ 50A#	820pF	J:±5% / K:±10%	30	1.0 ± 0.10	0.6 ± 0.10	0.6 ± 0.10	1000
[CM105C △ 102 □ 50A#	1nF	J:±5% / K:±10%]				





General CM02 Series Size (JIS Code): 01005(0402) # Packaging Code (Packaging quantity): H(20,000pcs.) / N(80,000pcs.) / P(40,000pcs.)

Dielectric	Doub Number	Consoitones	□:Tolerance	Voltage		Dimension		Tanδ
code	Part Number	Capacitance	□: i olerance	[V]	L[mm]	W[mm]	T[mm]	[%]
	CM02X5R101□16A#	100pF	K:± 10% / M:±20%					
	CM02X5R151□16A#	150pF	K:± 10% / M:± 20%					
	CM02X5R221□16A#	220pF	K:± 10% / M:± 20%]				
	CM02X5R331□16A#	330pF	K:±10% / M:±20%]				
	CM02X5R471□16A#	470pF	K:±10% / M:±20%]				
	CM02X5R681□16A#	680pF	K:±10% / M:±20%					
	CM02X5R102□16A#	1nF	K:±10% / M:±20%	16				
	CM02X5R152□16A#	1.5nF	K:±10% / M:±20%					
	CM02X5R222□16A#	2.2nF	K:±10% / M:±20%					
	CM02X5R332□16A#	3.3nF	K:±10% / M:±20%]				
X5R	CM02X5R472 ☐ 16A#	4.7nF	K:±10% / M:±20%]				
	CM02X5R682 ☐ 16A#	6.8nF	K:±10% / M:±20%					
	CM02X5R103□16A#	10nF	K:±10% / M:±20%					
	CM02X5R153□06A#	15nF	K:±10% / M:±20%					
	CM02X5R223□06A#	22nF	K:±10% / M:±20%]	0.4±0.02	0.2±0.02	0.2±0.02	12.5
	CM02X5R333□06A#	33nF	K:± 10% / M:±20%]	0.4 ± 0.02	0.2 ± 0.02	0.2 ± 0.02	12.5
	CM02X5R473□06A#	47nF	K:±10% / M:±20%	6.3				
	CM02X5R683□06A#	68nF	K:± 10% / M:±20%	0.5				
	CM02X5R104□06A#	100nF	K:± 10% / M:± 20%					
	CM02X5R224M06A#	220nF	M: ± 20%]				
	CM02X5R474M06A#	470nF	M: ± 20%]				
	CM02X7R101□16A#	100pF	K:± 10% / M:± 20%					
	CM02X7R151□16A#	150pF	K:± 10% / M:± 20%					
	CM02X7R221□16A#	220pF	K:± 10% / M:± 20%	1				
	CM02X7R331□16A#	330pF	K:±10% / M:±20%]				
X7R	CM02X7R471□16A#	470pF	K:± 10% / M:± 20%	16				
	CM02X7R681□16A#	680pF	K:±10% / M:±20%]				
	CM02X7R102□16A#	1nF	K:±10% / M:±20%					
	CM02X7R152□16A#	1.5nF	K:±10% / M:±20%]				
	CM02X7R222 ☐ 16A#	2.2nF	K:±10% / M:±20%					

General CM03 Series Size (JIS Code): 0201(0603) # Packaging Code (Packaging quantity): H(15,000pcs.) / N(50,000pcs.) / Q(30,000pcs.) / W(150,000pcs.)

Dielectric	D 1 N 1	0 "		Voltage		Dimension		Tanδ
code	Part Number	Capacitance	□:Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
	CM03X5R151□25A#	150pF	K:±10% / M:±20%					
	CM03X5R221□25A#	220pF	K: ± 10% / M: ± 20%	7				
	CM03X5R331□25A#	330pF	K:± 10% / M:± 20%	7				
	CM03X5R471□25A#	470pF	K: ± 10% / M: ± 20%	7			0.3±0.03	
	CM03X5R681□25A#	680pF	K: ± 10% / M: ± 20%	7	0.01.000			
	CM03X5R102□25A#	1nF	K: ± 10% / M: ± 20%	25		0.3±0.03		5.0
	CM03X5R152□25A#	1.5nF	K: ± 10% / M: ± 20%		0.6 ± 0.03	0.3±0.03	0.3 ± 0.03	5.0
	CM03X5R222□25A#	2.2nF	K: ± 10% / M: ± 20%	7				
	CM03X5R332□25A#	3.3nF	K: ± 10% / M: ± 20%	7				
	CM03X5R472□25A#	4.7nF	K: ± 10% / M: ± 20%	7				
	CM03X5R682□25A#	6.8nF	K: ± 10% / M: ± 20%	7				
	CM03X5R103□25A#	10nF	K:±10% / M:±20%					
X5R	CM03X5R153□10A#	15nF	K: ± 10% / M: ± 20%					
Yok	CM03X5R223 ☐ 10A#	22nF	K: ± 10% / M: ± 20%					
	CM03X5R333 □ 10A#	33nF	K: ± 10% / M: ± 20%	7				
	CM03X5R473 ☐ 10A#	47nF	K:±10% / M:±20%	10	0.6 ± 0.03	0.3 ± 0.03	0.3 ± 0.03	10.0
	CM03X5R683 ☐ 10A#	68nF	K: ± 10% / M: ± 20%					
	CM03X5R104□10A#	100nF	K: ± 10% / M: ± 20%					
	CM03X5R224□10A#	220nF	K: ± 10% / M: ± 20%					
	CM03X5R474□06A#	470nF	K: ± 10% / M: ± 20%	6.3	0.6 ± 0.03	0.3 ± 0.03	0.3 ± 0.03	12.5
	CM03X5R105M16A#	1	M:±20%	16	0.6 ± 0.09	0.3±0.09	0.3±0.09	20.0
	CM03X5R105M06A#	- 1μF	M: ± 20%	6.3	0.6 ± 0.05	0.3±0.05	0.3 ± 0.05	12.5
	CM03X5R225M10AH			10	0.6 ± 0.09	0.3 ± 0.09	0.3 ± 0.09	15.0
	CM03X5R225M06AH	2.2µF	M: ± 20%	6.3	0.6 ± 0.09	0.3 ± 0.09	0.3±0.09	12.5
	CM03X5R225M06A#035]		0.5	0.6 ± 0.05	0.3 ± 0.05	0.3 ± 0.05	12.5
	CM03X5R475M04AH	4.7µF	M: ± 20%	4	0.6 ± 0.09	0.3 ± 0.09	0.3 ± 0.09	12.5
	CM03X7R151□25A#	150pF	K:±10% / M:±20%					
	CM03X7R221□25A#	220pF	K:±10% / M:±20%	25	0.6 ± 0.03	0.3 ± 0.03	0.3 ± 0.03	3.5
	CM03X7R331□25A#	330pF	K:±10% / M:±20%					
	CM03X7R471□16A#	470pF	K:±10% / M:±20%					
	CM03X7R681□16A#	680pF	K:±10% / M:±20%	16	0.6 ± 0.03	0.3 ± 0.03	0.3 ± 0.03	3.5
X7R	CM03X7R102□16A#	1nF	K:±10% / M:±20%					
^/K	CM03X7R152□10A#	1.5nF	K:±10% / M:±20%					
	CM03X7R222 □ 10A#	2.2nF	K:±10% / M:±20%					
	CM03X7R332 □ 10A#	3.3nF	K:±10% / M:±20%	10	0.6±0.03	0.3±0.03	0.3±0.03	5.0
	CM03X7R472 □ 10A#	4.7nF	K:±10% / M:±20%	7 10	0.0 ± 0.03	0.5 ± 0.05	0.5 ± 0.05	5.0
	CM03X7R682 ☐ 10A#	6.8nF	K:±10% / M:±20%		1			
	CM03X7R103 ☐ 10A#	10nF	K:±10% / M:±20%					





General CM05 Series Size (JIS Code): 0402(1005) # Packaging Code (Packaging quantity): H(10,000pcs.) / N(50,000pcs.) / Q(20,000pcs.) / W(100,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tan δ
code	Fart Number	Capacitance	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
	CM05X5R104□25A#	100nF	K:± 10% / M:± 20%	25	1.0 ± 0.05	0.5 ± 0.05	0.5 ± 0.05	5.0
	CM05X5R224□16A#	220nF	K:± 10% / M:± 20%	16	1.0 ± 0.05	0.5 ± 0.05	0.5 ± 0.05	12.5
	CM05X5R474 ☐ 10A#	470nF	K:± 10% / M:±20%	10	1.0 ± 0.05	0.5 ± 0.05	0.5 ± 0.05	12.5
	CM05X5R474□06A#	4700		6.3	1.0 ± 0.05	0.5 ± 0.05	0.5 ± 0.05	10.0
	CM05X5R105□35A#			35				
	CM05X5R105□25A#]	K:±10% / M:±20%	25]		0.5±0.05	
	CM05X5R105 ☐ 16A#	1μF		16	1.0 ± 0.05	0.5 ± 0.05		10.0
X5R	CM05X5R105 ☐ 10A#			10				
XJIX	CM05X5R105□06A#			6.3				
	CM05X5R225 ☐ 10A#	2.2uF	K:±10% / M:±20%	10	1.0 ± 0.05	0.5±0.05	0.5±0.05	12.5
	CM05X5R225□06A#	2.2μΓ	N.± 10% / W.± 20%	6.3	1.0 ± 0.05		0.5 ± 0.05	12.5
	CM05X5R475M16A#	4.7uF	M:±20%	16	1.0 ± 0.20	0.5 ± 0.20	0.5 ± 0.20	12.5
	CM05X5R475M06A#	4.7µF	IVI. ± 20/6	6.3	1.0 ± 0.15	0.5 ± 0.15	0.5 ± 0.15	12.5
1	CM05X5R106M06A#	10μF	M: ± 20%	6.3	1.0 ± 0.20	0.5 ± 0.20	0.5 ± 0.20	12.5
	CM05X5R156M04A#	15µF	M:±20%	4	1.0 ± 0.15	0.5 ± 0.15	0.5±0.15	12.5
	CM05X5R226M04A#	22µF	IVI. ± 20/6	4	1.0 ± 0.20	0.5 ± 0.20	0.5 ± 0.20	12.0
X7R	CM05X7R104□25A#	100nF	K:± 10% / M:±20%	25	1.0 ± 0.05	0.5 ± 0.05	0.5 ± 0.05	12.5

General CM105 Series Size (JIS Code): 0603(1608) # Packaging Code (Packaging quantity): T(4,000pcs.) / L(10,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tan δ
code	r ai t Number	Capacitarice	□. Toler arice	[V]	L[mm]	W[mm]	T[mm]	[%]
	CM105X5R105□25A#	1µF	K:± 10% / M:±20%	25	1.6±0.15	0.8±0.15	0.8 ± 0.15	12.5
	CM105X5R225□16A#	2.2µF	$K:\pm 10\% / M:\pm 20\%$	16	1.6 ± 0.10	0.8 ± 0.10	0.8 ± 0.10	12.5
X5R	CM105X5R475□10A#	4.7µF	K:±10% / M:±20%	10	1.6 ± 0.15	0.8±0.15	0.8 ± 0.15	12.5
	CM105X5R475□06A#			6.3	1.6 ± 0.15	0.8±0.15	0.8 ± 0.15	7.5
	CM105X5R106M06A#	10µF	M: ± 20%	6.3	1.6 ± 0.15	0.8±0.15	0.8 ± 0.15	12.5
	CM105X7R105□16A#	1uF	K:± 10% / M:± 20%	16	1.6±0.10	0.8±0.10	0.8±0.10	12.5
X7R	CM105X7R105□10A#	ΙμΓ	N. ± 10% / W. ± 20%	10	1.0 ± 0.10	0.6 ± 0.10	0.6 ± 0.10	12.5
	CM105X7R225□06A#	2.2µF	K:± 10% / M:±20%	6.3	1.6 ± 0.15	0.8±0.15	0.8 ± 0.15	12.5

General CM21 Series Size (JIS Code): 0805(2012) # Packaging Code (Packaging quantity): T(3,000pcs.) / L(10,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tanδ
code	Fart Number	Capacitarice	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
	CM21X5R105□50A#	1uF	K:± 10% / M:± 20%	50	2.0 ± 0.10	1.25±0.10	1.25±0.10	12.5
	CM21X5R105□25A#	IμΓ	K.± 10% / W.± 20%	25	2.0 ± 0.10	1.25±0.10	1.25±0.10	5.0
	CM21X5R225□25A#	2.2uF	K:± 10% / M:± 20%	25	2.0 ± 0.20	1.25 ± 0.20	1.25 ± 0.20	12.5
	CM21X5R225 ☐ 16A#	2.2μΓ	K.± 10% / W.± 20%	16	2.0 ± 0.10	1.25±0.10	1.25±0.10	5.0
X5R	CM21X5R475□25A#			25	2.0 ± 0.20	1.25 ± 0.20	1.25 ± 0.20	12.5
	CM21X5R475□16A#	4.7µF	K:±10% / M:±20%	16	2.0 ± 0.15	1.25±0.15	1.25±0.15	12.5
	CM21X5R475□10A#			10	2.0 ± 0.10	1.25 ± 0.10	1.25 ± 0.10	7.0
	CM21X5R106□16A#	- 10μF	K:±10% / M:±20%	16	2.0 ± 0.20	1.25 ± 0.20	1.25 ± 0.20	12.5
	CM21X5R106□06A#			6.3	2.0 ± 0.20	1.25 ± 0.20	1.25 ± 0.20	7.5
	CM21X7R105□50A#			50	2.0 ± 0.20	1.25 ± 0.20	1.25 ± 0.20	5.0
	CM21X7R105□25A#	1µF	$K:\pm 10\% / M:\pm 20\%$	25	2.0 ± 0.10	1.25 ± 0.10	1.25±0.10	12.5
	CM21X7R105□10A#			10	2.0 ± 0.10	1.25 ± 0.10	1.25 ± 0.10	5.0
X7R	CM21X7R225□25A#	2.2µF	K:±10% / M:±20%	25	2.0 ± 0.20	1.25 ± 0.20	1.25 ± 0.20	12.5
	CM21X7R475□16A#	4.7µF	K:±10% / M:±20%	16	2.0 ± 0.20	1.25 ± 0.20	1.25 ± 0.20	12.5
	CM21X7R106□10A#	10uF	K:±10% / M:±20%	10	2.0±0.20	1.25±0.20	1.25 ± 0.20	12.5
	CM21X7R106□06A#	ΤΟμί	11 10/0 / WL-20/0	6.3	2.0 - 0.20	1.20 = 0.20	1.20 = 0.20	12.0

General CM316 Series Size (JIS Code): 1206(3216) # Packaging Code (Packaging quantity): T(2,500pcs.) / L(5,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tanδ
code		Capacitarice	□. Foler affice	[V]	L[mm]	W[mm]	T[mm]	[%]
	CM316X5R225 ☐ 100A#	2.2µF	F K:± 10% / M:± 20%	100	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	5.0
	CM316X5R225□25A#	2.2μΓ	K.± 10% / W.± 20%	25	3.2 ± 0.20	1.6 ± 0.15	1.6 ± 0.15	5.0
	CM316X5R475□50A#	4.7uF	K:± 10% / M:± 20%	50	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	5.0
	CM316X5R475□25A#	4.7μι	10. ± 10/8 / W. ± 20/8	25	3.2 ± 0.20	1.6 ± 0.15	1.6 ± 0.15	5.0
X5R	CM316X5R106□25A#			25	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	12.5
	CM316X5R106□16A#	10μF	K:±10% / M:±20%	16	3.2 ± 0.20	1.6±0.15	1.6 ± 0.15	5.0
	CM316X5R106□10A#	ļ		10	3.2 ± 0.20	1.6±0.15	1.6 ± 0.15	7.0
	CM316X5R226□16A#	22µF	K:±10% / M:±20%	16	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	12.5
	CM316X5R226□06A#			6.3	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	7.5
	CM316X7R475□50A#	4.7uF	K:±10% / M:±20%	50	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	5.0
	CM316X7R475□25A#	4.7μι	10. ± 10/8 / W. ± 20/8	25	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	12.5
X7R	CM316X7R106□25A#	10uF	K:±10% / M:±20%	25	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	5.0
A/K	CM316X7R106□16A#	ΤΟμΓ	N. ± 10% / W. ± 20%	16	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	12.5
	CM316X7R226□10A#	22uF	K:±10% / M:±20%	10	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	7.5
	CM316X7R226□06A#	· ·		6.3	3.2 ± 0.20	1.6 ± 0.20	1.6 ± 0.20	12.5
X7S	CM316X7S225□100A#	2.2µF	K:±10% / M:±20%	100	3.2±0.20	1.6±0.20	1.6 ± 0.20	5.0

General CM316 Series Size (JIS Code): 1206(3216) # Packaging Code (Packaging quantity): T(2,000pcs.)

	Dielectric	Part Number	Consoitance	□:Tolerance	Voltage		Dimension		Tanδ
	code	Part Number	Capacitance	□:1 olerance	[V]	L[mm]	W[mm]	T[mm]	[%]
[X7S	CM316X7S475□100AT	4.7µF	K:±10% / M:±20%	100	3.2 ± 0.30	1.6±0.30	1.6±0.30	5.0





General CM32 Series Size (JIS Code): 1210(3225) # Packaging Code (Packaging quantity): T(1,000pcs.) / L(4,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tanδ
code	Fart Number	Capacitance	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
	CM32X5R475□25A#	4.7μF	K:±10% / M:±20%	25	3.2 ± 0.30	2.5 ± 0.20	2.5±0.20	5.0
	CM32X5R106□50A#			50	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	5.0
	CM32X5R106□25A#	10μF	$K:\pm 10\% / M:\pm 20\%$	25	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	12.5
VED	CM32X5R106□16A#]		16	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	5.0
X5R	CM32X5R226□25A#		K:±10% / M:±20%	25	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	12.5
	CM32X5R226 ☐ 16A#	22µF		16	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	5.0
	CM32X5R226 ☐ 10A#			10	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	7.0
	CM32X5R476□06A#	47µF	K:± 10% / M:±20%	6.3	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	7.5
	CM32X7R475□16A#	4.7µF	K:± 10% / M:±20%	16	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	2.5
X7R	CM32X7R106□50A#	10uF	K:±10% / M:±20%	50	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	5.0
_ ^/K	CM32X7R106□25A#	ΙΟμΕ	K: ± 10% / W: ± 20%	25	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	12.5
	CM32X7R226 ☐ 16A#	22µF	K:±10% / M:±20%	16	3.2 ± 0.30	2.5 ± 0.20	2.5 ± 0.20	12.5

Low Profile CT03 Series Size (JIS Code): 0201(0603) # Packaging Code (Packaging quantity): H(15,000pcs.) / N(50,000pcs.) / Q(30,000pcs.) / N(150,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tanδ
code	Fart Number	Capacitance	□. I oler arice	[V]	L[mm]	W[mm]	T[mm]	[%]
X5R	CT03X5R104□06A#022	100nF	K:±10% / M:±20%	6.3	0.6 ± 0.03	0.3 ± 0.03	0.22max	12.5
No.K	CT03X5R105M06AH025	1µF	M:±20%	6.3	0.6 ± 0.09	0.3 ± 0.09	0.25max	12.5

Low Profile CT05 Series Size (JIS Code): 0402(1005) # Packaging Code (Packaging quantity): H(10,000pcs.) / N(50,000pcs.) / Q(20,000pcs.) / N(100,000pcs.)

D	ielectric	Part Number Capacitance		□.Toloropoo	Voltage		Tan δ		
	code	Part Number	Capacitarice	□:Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
		CT05X5R105M06A#022	1uF	M: ± 20%	6.3	1.0±0.05	0.5±0.05	0.22max	12.5
	X5R	CT05X5R105□06A#033	Тμг	K:± 10% / M:± 20%	0.5	1.0 ± 0.03	0.5 ± 0.05	0.33max	12.5
	ASK	CT05X5R225M06A#033	2.2µF	M: ± 20%	6.3	1.0 ± 0.05	0.5 ± 0.05	0.33max	12.5
		CT05X5R475M06AH033	4.7μF	M: ± 20%	6.3	1.0 ± 0.20	0.5 ± 0.20	0.33max	15.0

Low Profile CT105 Series Size (JIS Code): 0603(1608) # Packaging Code (Packaging quantity): H(4,000pcs.) / N(10,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tanδ
code	Fart Number	Capacitarice	□. I oler arice	[V]	L[mm]	W[mm]	T[mm]	[%]
X5R	CT105X5R105□16A#055	1µF	K:± 10%/M:±20%	16	1.6±0.10	0.8±0.10	0.55max	12.5

Low Profile CT21 Series Size (JIS Code): 0805(2012) # Packaging Code (Packaging quantity): H(4,000pcs.) / N(10,000pcs.)

Dielectric code	Part Number	Capacitance	□:Tolerance	Voltage [V]	L[mm]	Dimension W[mm]	T[mm]	Tan δ [%]
	CT21X5R105□25A#095	1µF	K:± 10% / M:± 20%	25	2.0±0.10	1.25±0.10	0.95max	5.0
X5R	CT21X5R225□50A#095	2.2µF	K:±10% / M:±20%	50	2.0 ± 0.20	1.25 ± 0.20	0.95max	5.0
	CT21X5R475□16A#095	4.7µF	K:± 10% / M:± 20%	16	2.0±0.15	1.25 ± 0.15	0.95max	12.5

High-Q CU02 Series Size (JIS Code): 01005(0402) # Packaging Code (Packaging quantity): H(20,000pcs.) / N(80,000pcs.) / P(40,000pcs.)

Dielectric code	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		0
СФ	Part Number	Capacitance	□: i olerance	[V]	L[mm]	W[mm]	T[mm]	Q
	CU02C △R20 ☐ 16A#	0.2pF	B: ±0.1pF / C: ±0.25pF					404
	CU02C △R50 □ 16A#	0.5pF	B: $\pm 0.1pF / C$: $\pm 0.25pF$]				410
	CU02C △ 1R0 □ 16A#	1pF	$B:\pm 0.1pF / C:\pm 0.25pF$					420
	CU02C △ 1R5 □ 16A#	1.5pF	$B:\pm 0.1pF / C:\pm 0.25pF$					430
	CU02C △ 2R0 □ 16A#	2pF	$B:\pm 0.1pF / C:\pm 0.25pF$					440
	CU02C ∆ 3R0 □ 16A#	3pF	B: $\pm 0.1pF / C$: $\pm 0.25pF$	16			0.2±0.02	460
	CU02C △ 4R0 □ 16A#	4pF	$B:\pm 0.1pF / C:\pm 0.25pF$					480
	CU02C ∆ 5R0 □ 16A#	5pF	$B:\pm 0.1pF / C:\pm 0.25pF$					500
CG/CH	CU02C △ 6R0 □ 16A#	6pF	$C:\pm 0.25pF / D:\pm 0.5pF$		0.4±0.02	0.2±0.02		520
	CU02C △ 7R0 □ 16A#	7pF	$C:\pm 0.25pF / D:\pm 0.5pF$					540
	CU02C △ 8R0 □ 16A#	8pF	$C:\pm 0.25pF / D:\pm 0.5pF$]				560
	CU02C △ 9R0 □ 16A#	9pF	$C:\pm 0.25pF / D:\pm 0.5pF$]				580
	CU02C △ 100 □ 16A#	10pF	J:±5% / K:±10%					600
	CU02C △ 120 □ 16A#	12pF	J:±5% / K:±10%					640
	CU02C △ 150 □ 16A#	15pF	J:±5% / K:±10%	1				700
	CU02C △ 180 □ 16A#	18pF	J:±5% / K:±10%]				760
	CU02C △ 220 □ 16A#	22pF	J:±5% / K:±10%]				840





Au TerminationAT02 Series Size (JIS Code): 01005(0402) ♦ Termination Code: G(AuSn solder and conductive adhesive.)

Packaging Code (Packaging quantity): H(20,000pcs.)

Dielectric	Part Number	Canacitance	\(\tau_i\tau	Voltage		Dimension		Tanδ
code	Part Number	Capacitance	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
X5R	AT02X5R104□06GH	100nF	K:± 10% / M:± 20%	6.3	0.4 ± 0.02	0.2 ± 0.02	0.2 ± 0.02	12.5

Au TerminationAT03 Series Size (JIS Code): 0201(0603) Packaging Code (Packaging quantity): H(15,000pcs.) ♦ Termination Code: G (AuSn solder and conductive adhesive.) / K (Wire bonding and conductive adhesive.)

Dielectric	ctric Part Number Capacitance D:Tolerance		Voltage		Tanδ			
code	rait Number	Capacitarice	□. I olei arice	[V]	L[mm]	W[mm]	T[mm]	[%]
	AT03X5R474□06♦H	470nF	K:± 10% / M:± 20%		0.6 ± 0.03	0.3 ± 0.03	0.3 ± 0.03	
X5R	AT03X5R105□06♦H	1µF	K:± 10% / M:± 20%	6.3	0.6 ± 0.05	0.3 ± 0.05	0.3 ± 0.05	12.5
	AT03X5R225□06♦H	2.2uF	K:±10% / M:±20%]	0.6±0.09	0.3±0.09	0.3±0.09	

Au TerminationAT05 Series Size (JIS Code): 0402(1005) Packaging Code (Packaging quantity): H(10,000pcs.) Termination Code: G (AuSn solder and conductive adhesive.) / K (Wire bonding and conductive adhesive.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tan δ
code	Fart Number	Capacitarice	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
VED	AT05X5R474□06♦H	470nF	K:± 10% / M:± 20%	6.2	1.0±0.05	0.5±0.05	0.5±0.05	10.0
X5R	AT05X5R105□06♦H	1uF	K:± 10% / M:± 20%	0.3	1.0 ± 0.05	0.5 ± 0.05	0.5 ± 0.05	10.0

Soft Termination ST03 Series Size (JIS Code): 0201(0603) # Packaging Code (Packaging quantity): H(15,000pcs.) / N(50,000pcs.) / Q(30,000pcs.) / W(150,000pcs.)

Dielectric	ctric Part Number Capacitance □:Toleran		□:Tolerance	Voltage		Tanδ		
code	Fart Number	Capacitance	□. I oler arice	[V]	L[mm]	W[mm]	T[mm]	[%]
X5R	ST03X5R105M06S#	1μF	M:±20%	6.3	0.6 ± 0.05	0.3 ± 0.05	0.3±0.05	12.5
\ \2K	ST03X5R225M04SH	2.2uF	M:±20%	4	0.6 ± 0.10	0.3 ± 0.10	0.3 ± 0.10	12.5

Soft Termination ST05 Series Size (JIS Code): 0402(1005) # Packaging Code (Packaging quantity): H(10,000pcs.) / N(50,000pcs.) / Q(20,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tanδ
code	Fart Number	Capacitance	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
	ST05X5R225□10S#	2.2µF	K:±10% / M:±20%	10	1.0±0.07	0.5 ± 0.07	0.5±0.07	12.5
X5R	ST05X5R475M06S#	4.7µF	M:±20%	6.3	1.0 ± 0.15	0.5 ± 0.15	0.5 ± 0.15	12.5
	ST05X5R106M06SH	10μF	W: ± 20%	0.3	1.0 ± 0.20	0.5 ± 0.20	0.5 ± 0.20	12.5

High Voltage CF21 Series Size (JIS Code): 0805(2012) # Packaging Code (Packaging quantity): T(4,000pcs.) / L(10,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension	Tan δ	
code	Fart Number	Capacitance	□. Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
X7R	CF21X7R221□250A#	220pF	K:± 10% / M:± 20%	250	2.0±0.10	1.25±0.10	0.85±0.10	2.5
N/K	CF21X7R471□250A#	470pF	K: ± 10% / M: ± 20%	250	2.0 ± 0.10	1.25 ± 0.10	0.65 ± 0.10	2.5

High Voltage CF21 Series Size (JIS Code): 0805(2012) # Packaging Code (Packaging quantity): T(3,000pcs.) / L(10,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tanδ
code	T are Harrison	Oupaortarioo	E. Folor arioc	[V]	L[mm]	W[mm]	T[mm]	[%]
	CF21X7R102□250A#	1nF	K:± 10% / M:± 20%					
	CF21X7R222□250A#	$21X7R222\square 250A\#$ $2.2nF$ $K:\pm 10\% / M:\pm 20\%$ 250 $2.0\pm 0\%$	2.0 ± 0.10	1.25±0.10	1.05 ± 0.10	2.5		
X7R	CF21X7R472□250A#	4.7nF	K:±10% / M:±20%					
	CF21X7R103□250A#	10nF	K:± 10% / M:±20%	250	2.0±0.10	1.25±0.10	1.25±0.10	2.5
	CF21X7R223□250A#	22nF	K:± 10% / M:±20%	250	2.0 ± 0.10	1.25 ± 0.10	1.25 ± 0.10	2.5

High Voltage CF316 Series Size (JIS Code): 1206(3216) # Packaging Code (Packaging quantity): T(3,000pcs.) / L(10,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage		Dimension		Tanδ
code	Fart Number	Capacitance	□. I oler arice	[V]	L[mm]	W[mm]	T[mm]	[%]
	CF316X7R221□1000A#	220pF					1.15±0.10	
	CF316X7R471□1000A#	470pF	$K:\pm 10\% / M:\pm 20\%$	1000	3.2±0.20	1.6±0.15	1.15 ± 0.10	2.5
	CF316X7R102□1000A#	1nF					1.25 ± 0.10	
X7R	CF316X7R222□630A#	2.2nF						
\/\K	CF316X7R472□630A#	4.7nF	$K:\pm 10\% / M:\pm 20\%$	630	3.2 ± 0.20	1.6 ± 0.15	1.25 ± 0.10	2.5
	CF316X7R103□630A#	10nF						
	CF316X7R103□250A#	10nF	K. + 10% / M. + 20%	250	3.2±0.20	1.6±0.15	1.15±0.10	2.5
	CF316X7R223□250A#	22nF	K:±10% / M:±20%	250	3.2 ± 0.20		1.15 ± 0.10	2.5





High Voltage CF316 Series Size (JIS Code): 1206(3216) # Packaging Code (Packaging quantity): T(2,500pcs.) / L(5,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage	Dimension			Tan δ
code	Fart Number	Capacitance	□.1 oler arice	[V]	L[mm]	W[mm]	T[mm]	[%]
	CF316X7R222 1000A#		K:±10% / M:±20%	1000	3.2 ± 0.20	1.6±0.15	1.6 ± 0.15	2.5
X7R	CF316X7R223□630A#	22nF		630	3.2 ± 0.20	1.6 ± 0.15	1.6 ± 0.15	2.5
AIR	CF316X7R473□250A#	47nF	I/ ± 100/ / M ± 000/	050	204000	1.6±0.15	1.6±0.15	2.5
	CF316X7R104□250A#	100nF	K:±10% / M:±20%	250	3.2±0.20	1.0 ± 0.15	1.0 ± 0.15	2.5

High Voltage CF32 Series Size (JIS Code): 1210(3225) # Packaging Code (Packaging quantity): T(2,500pcs.) / L(5,000pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage	Dimension			Tan δ
code	Fart Number	Capacitarice	□. Foler affice	[V]	L[mm]	W[mm]	T[mm]	[%]
X7R	CF32X7R472□1000A#	4.7nF	K:±10% / M:±20%	1000	3.2 ± 0.30	2.5 ± 0.20	1.6 ± 0.15	2.5
\/\K	CF32X7R223□630A#	22nF	N. ± 10/6 / W. ± 20/6	630	3.2 ± 0.30	2.5 ± 0.20	1.6±0.15	2.5

High Voltage CF32 Series Size (JIS Code): 1210(3225) # Packaging Code (Packaging quantity): T(2,000pcs.) / L(5,000pcs.)

Dielectric	Part Number	Consoitones	□:Tolerance	Voltage	Dimension			Tanδ
code	Fart Number	Capacitance	□. Foler affice	[V]	L[mm]	W[mm]	T[mm]	[%]
X7R	CF32X7R473□630A#	47nF	K:±10% / M:±20%	630	3.2 ± 0.30	2.5 ± 0.20	2.0 ± 0.20	2.5
AIR	CF32X7R104□250A#	100nF	N: ± 10% / IVI: ± 20%	250	3.2 ± 0.30	2.5 ± 0.20	2.0 ± 0.20	2.5

High Voltage CF42 Series Size (JIS Code): 1808(4520) Packaging Code (Packaging quantity): T(2,000pcs.)

Dielectric	Part Number Capacitance Dimens		Dimension		Tan δ			
code	Part Number	Capacitarice	□: Tolerance	[V]	L[mm]	W[mm]	T[mm]	[%]
	CF42X7R102□2000AT	1nF	K:±10% / M:±20%	2000	4.5 ± 0.20	2.0 ± 0.20	2.2 max	2.5
X7R	CF42X7R222 ☐ 1000AT	2.2nF	K:±10% / M:±20%					
	CF42X7R472 ☐ 1000AT	4.7nF	K:±10% / M:±20%	1000	4.5 ± 0.20	2.0 ± 0.20	2.2 max	2.5
	CF42X7R103 ☐ 1000AT	10nF	K:±10% / M:±20%]				

High Voltage CF43 Series Size (JIS Code): 1812(4532) Packaging Code (Packaging quantity): T(500pcs.)

Dielectric	Part Number	Capacitance	□:Tolerance	Voltage	Dimension			Tan δ
code	Fart Number	Capacitarice	□. Toler affice	[V]	L[mm]	W[mm]	T[mm]	[%]
	CF43X7R222□2000AT	2.2nF	K: ± 10% / M: ± 20%	2000	4.5 ± 0.30	3.2 ± 0.20	2.5 max	2.5
X7R	CF43X7R223 ☐ 1000AT	22nF	K:±10% / M:±20%	1000	4.5 ± 0.30	3.2 ± 0.20	2.5 max	2.5
A/K	CF43X7R104□630AT	100nF	K:±10% / M:±20%	630	4.5 ± 0.30	3.2 ± 0.20	2.5 max	2.5
	CF43X7R224□250AT	220nF	K·+ 10% / M·+ 20%	250	45+030	32+020	2.5 max	2.5

Three Terminal Capacitors KNH05 Series Size (JIS Code): 0402(1005) Packaging Code (Packaging quantity): H(10,000pcs.)

Dielectric	Part Number	Consoitance	□:Tolerance	Voltage		Dimension		Tan δ
code	Fart Number	Capacitance	□. Foler affice	[V]	L[mm]	W[mm]	T[mm]	[%]
X5R	KNH05X5R435M04AH	4.3µF	M: ± 20%	4	1.0 ± 0.10	0.5 ± 0.20	0.50 max	_
XSK	KNILIOE VED 106M04ALI	10uE	M+ + 20%] 4	10+020	0.5 ± 0.20	0 5 + 0 20	_

Notes for Using the Catalog

- 1. Specifications described in this catalog are for references. Products specifications shall be based on written documents agreed by each party.
- 2. Contents in this catalog are subject to change without notice. It is recommended to confirm the latest information at the time of usage. Also, Kyocera Electronic Components Catalog is revised once a year. We may not be able to accept requests based on old catalogs.
- 3. Products in this catalog are intended to be used in general electronic equipment such as office equipment, audio and visual equipment, communication equipment, measurement instrument and home appliances. It is absolutely recommended to consult with our sales representatives in advance upon planning to use our products in applications which require extremely high quality and reliability such as aircraft and aerospace equipment, traffic systems, safety systems, power plant and medical equipment including life maintenance systems.
- 4. Even though we strive for improvements of quality and reliability of products, it is requested to design with enough safety margin in equipment or systems in order not to threaten human lives directly or damage human bodies or properties by an accidental result of products.
- 5. It is requested to design based on guaranteed specifications for such as maximum ratings, operating voltage and operating temperature. It is not the scope of our guarantee for unsatisfactory results due to misuse or inadequate usage of products in the catalog.
- 6. Operation summaries and circuit examples in this catalog are intended to explain typical operation and usage of the product. It is recommended to perform circuit and assembly design considering surrounding conditions upon using products in this catalog.
- 7. Technical information described in this catalog is meant to explain typical operations and applications of products, and it is not intended to guarantee or license intellectual properties or other industrial rights of the third party or Kyocera.
- 8. Trademarks, logos and brand names used in this catalog are owned by Kyocera or the corresponding third party.
- 9. Certain products in this catalog are subject to the Foreign Exchange and Foreign Trade Control Act of Japan, and require the license from Japanese Government upon exporting the restricted products and technical information under the law.

 Besides, it is requested not to use products and technical information in the catalog for the development and/or manufacture of weapons of mass destruction or other conventional weapons, nor to provide
- 10. It is prohibited to reprint and reproduce a part or whole of this catalog without permission.
- 11. Contents described herein are as of February 2018.

Design Tool Introduction



Search ceramic capacitors by parameters.

them to any third party with the possibility of having such purposes.

http://prdct-search.kyocera.co.jp/electro-mlcc-en/







CAT12T1802TH2785E

The information contained in this catalog is current as of February 2018.

单击下面可查看定价,库存,交付和生命周期等信息

>>Kyocera(京瓷)